(54) Title: SYSTEM AND METHOD FOR COMPENSATING HEARING DEFICIENCES

(57) Abstract

A hearing aid (12) including a microphone (75) for generating an electrical output from sounds external to a user of the hearing aid (12), an electrically driven receiver (79, 81) for emitting sound into the ear of the user of the hearing aid (12), and circuitry (61) for driving the receiver. The circuitry (61) drives the receiver (79, 81) in a self-generating mode activated by a first set of signals supplied externally of the hearing aid to cause the receiver (79, 81) to emit sound having at least one parameter controlled by the first set of externally supplied signals and then drives the receiver in a filtering mode, activated by a second set of signals supplied externally of the hearing aid (12), with the output of the external microphone (75) filtered according to filter parameters established by the second set of the externally supplied signals. Other forms of the hearing aid (12), apparatus (14) for supplying the sets of signals to the hearing aid (12) in a total system (10), and methods of operation are also described.

System and method for compensating hearing
deficiences.

Background of the Invention

5

This invention relates to hearing aids, systems for
compensating hearing deficiencies of a patient, signal supply-
ing apparatus for use in such systems, and methods for compen-
sating hearing deficiencies. More specifically, the invention
relates to hearing aids which can respond to externally sup-
plied electrical signals or generate signals for external use,
10   or both, and to apparatus for externally supplying the elec-
trical signals, and methods of operation of the signal supply-
ing apparatus when connected to a hearing aid.

A person's ability to hear speech and other sounds
well enough to understand them is clearly important in employ-
15   ment and many other daily life activities. Professional ser-
vices which have as their goal to compensate or at least.
ameliorate hearing deficiencies of hearing impaired persons
are consequently important to the community. Unfortunately,
such services have in the past been subject to practical
20   difficulties and errors.

For example, in a known approach, the patient's
residual hearing has been measured and then a hearing aid has
been selected from among different manufacturers and models.
The length of time spent in measuring the patient's residual
25   hearing and in selecting a "best" hearing aid from among the
different manufacturers and models has been burdensomely long
(about two hours). Moreover, the hearing aid selected during
the evaluation is often not the actual instrument purchased
and·then worn by the patient, but is the same model and there-
30   fore is representative. Even if a particular hearing aid
meets ANSI-1982 specifications, the amplification of the pur-
chased hearing aid instrument can, because of manufacturing

2

variations, differ considerably from that of the trial aid used during the evaluation. Ear canal and earmold effects, which can modify gain and maximum power output by as much as 30 dB, have been difficult to determine precisely and quickly
5 on an individual basis. It has been difficult to accurately measure the patient's residual hearing and the performance of even the trial aid due to assumptions that are conventionally made in calibrating the acoustic characteristics of. the audio-meter and hearing aids, introducing error into the estimation
10 of sound pressure levels in the patient's ear.

A large amount of information is required in order to simply repeat a particular test condition. Recordkeeping has become difficult and expensive to implement in a reason-able amount of time. And most of the foregoing problems recur
15 should it be necessary to replace a lost or damaged hearing aid.

Summary of the Invention

Among the objects of the present invention is to provide improved hearing aids that can be accurately custom
20 fitted in performance characteristics to each individual patient and then worn home; to provide improved hearing aids that improve the accuracy of hearing measurements and hearing aid fitting; to provide hearing aids of the foregoing type wherein at least one or more of the hearing aid improvements
25 made to achieve advantages in the fitting of the hearing aid also keeps the fit optimal after the fitting procedure is over and the patient has gone home; to provide improved hearing aids which respond to externally supplied electrical signals or generate signals for external use, or both; to provide
30 improved apparatus and methods for externally supplying the electrical signals to such a hearing aid; to provide improved

3

hearing aid fitting systems including the foregoing apparatus
communicating with such a hearing aid; to provide improved
methods, apparatus and systems for controlling the functions
and characteristics of a hearing aid; to provide improved
5 methods, apparatus and systems for fitting a hearing aid which
can automatically take into account manufacturing variations
in at least some components of the hearing aid; to provide
improved hearing aids which have low noise and low distortion;
to provide improved methods, apparatus and systems for auto-
10 matically determining the patient's hearing threshold, most
comfortable listening level, and uncomfortable listening
level; to provide improved hearing aids, apparatus, systems,
and methods that can compensate the hearing deficiencies of a
patient with an accuracy of fit more closely approximating a
15 research laboratory ideal fit; to provide improved apparatus,
systems and methods that can be used to fit hearing aids to
patients with at least comparable accuracy to conventional
fitting in significantly less time; to provide improved appa-
ratus, systems and methods to fit a hearing aid to a patient
20 that adaptively reach a final setting of the hearing aid that
yields maximum comfort and speech intelligibility for the
patient; to provide improved hearing aids that can be effi-
ciently replaced; and to provide improved hearing aids that
are economical, wearable, and reliable.
25   Other objects and features will be in part apparent
and in part pointed out hereinafter.
          Generally, and, in one form of the invention, a hear-
ing aid includes a microphone for generating an electrical
output from sounds external to a user of the hearing aid, an
30 electrically driven receiver for emitting sound into the ear
of the user of the hearing aid, and circuitry for driving the
receiver in a self-generating mode activated by a first set of
signals supplied externally of the hearing aid to cause the
receiver to emit sound having at least one parameter con-
35 trolled by the first set of externally supplied signals and

4

for then driving the receiver in a filtering mode, activated
by a second set of signals supplied externally of the hearing
aid, with the output of the external microphone filtered
according to filter parameters established by the second set
5   of the externally supplied signals.

Generally, and in another form of the invention a
hearing aid has a body adapted to be placed in communication
with an ear canal, and the hearing aid body has an external
microphone sensitive to external sound, and a receiver for
10   supplying sound to the ear canal. The hearing aid includes a
probe microphone in the hearing aid body for sensing the sound
present in the ear canal, and circuitry connected to the
external microphone and the probe microphone for driving the
receiver in response to both the external microphone and the
15   probe microphone, and for generating a digital signal for
external use in adjusting the performance of the hearing aid,
the digital signal representing at least one parameter of the
sound sensed by the probe microphone.

Generally, and in yet another form of the invention
20   the hearing aid includes the probe microphone and circuitry
connected to the external microphone for filtering, then lim-
iting, and then filtering the output of the external micro-
phone according to a set of internal parameters and for self-
adjusting at least one of the internal parameters as a func-
25   tion of the output of the probe microphone, thereby to drive
the receiver.

In general, and in an additional form of the inven-
tion, the hearing aid includes the probe microphone and digi-
tal computing circuitry in the hearing aid coupled to the
30   external microphone, to the probe microphone and to the
receiver. The digital computing circuitry is adapted for con-
nection to an external source of programming signals, and
loads and executes entire programs represented by the signals

5

and thereby utilizes the probe microphone, the external micro-
phone and the receiver for hearing testing and digital filter-
ing.

5   Generally, and in a system form of the invention for
compensating hearing deficiencies of a patient, the system
includes a hearing aid having an external microphone, program-
mable circuitry for filtering the output of the external
microphone, and a receiver driven by the programmable filter-
ing circuitry for emitting sounds into the ear of the patient.
10   The system has means for sensing responses of the patient to
sounds from the receiver. The system further includes appa-
ratus communicating with the hearing aid and the sensing
means, for selectively generating a first set of signals to
cause the programmable filtering circuitry in the hearing aid
15   to operate so that the receiver emits sounds having a parame-
ter controlled by the first set of signals, and for then gen-
erating in response to the sensing means a second set of sig-
nals determined from the controlled parameter and the
responses of the patient to the sounds with the controlled
20   parameter to establish filter parameters in the programmable
filtering circuitry to cause it to filter the output of the
external microphone and to drive the receiver with the fil-
tered output thereby ameliorating the hearing deficiencies of
the patient.

25   In general, and in another system form of the inven-
tion, the system includes a hearing aid having an external
microphone, a programmable digital computer in the hearing aid
and fed by the external microphone, a receiver fed by the pro-
grammable digital computer for emitting sounds into the ear of
30   the patient, and a probe microphone for sensing the actual
sound in the ear of the patient. The system further incorpo-
rates a data link and apparatus for selectively supplying at
least a first set and a subsequent second set of digital sig-
nals to the data link, the data link communicating the digital

6

signals to the programmable digital computer of the hearing
aid. The programmable digital computer in the hearing aid
comprises means for selectively driving the receiver so that
at least one sound for hearing testing is emitted into the ear
5   in response to the first set of digital signals, for supplying
to the data link a third set of digital signals representing a
parameter of the output of the probe microphone, and for sub-
sequently filtering the output of the external microphone in
response to the subsequently supplied second set of digital
10 signals to drive the receiver in a manner adapted for amelio-
rating the hearing deficiencies of the patient.

        Generally, and in a form of the invention for use in
a system including a hearing aid of the type described in the
previous paragraph, signal supplying apparatus includes inter-
15 face means for performing two-way digital serial communication
with the digital computer in the hearing aid and circuitry for
initiating transmission of a first set of signals from the
interface means to the hearing aid to cause the digital com-
puter in the hearing aid to operate so that the receiver emits
20 sounds having an adjustable parameter. The circuitry also
obtains, through the interface means, data representing values
of the adjustable parameter of the sounds as sensed by the
probe microphone, and then initiates transmission from the
interface means of a second set of signals determined at least
25 in part from the values of the parameter of the sensed sounds.
The second set of signals causes the digital computer in the
hearing aid to filter the output of the external microphone
and drive the receiver with the filtered output, thereby
. ameliorating the hearing deficiencies of the patient.
30   In general, a method form of the invention is used
for compensating hearing deficiencies of a patient with a
hearing aid having an external microphone, electronic cir-
cuitry for processing the output of the external microphone,
and a receiver driven by the electronic processing circuitry

7

for emitting sound into the ear of the patient. The method
includes the steps of selectively supplying a first set of
signals to the hearing aid to cause the electronic processing
circuitry to operate so that the receiver emits sound having a

5   parameter controlled by the first set of signals. Representa-
tions of responses of the patient to the sound are sensed and
electrically stored. Then a second set of signals is deter-
mined from the at least one controlled parameter of the sound
and the representations of the patient responses to the sound

10   with the controlled parameter. The second set of signals
causes the electronic processing circuitry to filter the out-
put of the external microphone and drive the receiver with the
filtered output, thereby ameliorating the hearing deficiencies
of the patient.

15   Brief Description of the Drawings

Fig. 1 is a block diagram of a system for compensat-
ing hearing deficiencies of a patient, the system including a
hearing aid and signal supplying apparatus according to the
invention;

20   Fig. 2 is a view of the exterior of a hearing aid
according to the invention for use in the system of Fig. 1;
Fig. 3 is a cross-section of a transducer module and
earmold part of the hearing aid of Fig. 2, which part is to be
put in the patient's ear;

25   Fig. 3A is a section on line 3A-3A of Fig. 3 illus-
trating channels in the ear mold part of the hearing aid of
Figs. 2 and 3;

Fig. 4 is a block diagram of the electronic
circuitry of the hearing aid of Fig. 2;

30   Fig. 5 is a flow diagram of operations according to
a method of the invention performed by a host computer in the
signal supplying apparatus of Fig. 1;

9

Fig. 6 is a flow diagram of operations of the host computer according to a method of the invention to calibrate for ear impedance;

5   Fig. 7 is a flow diagram of operations of the host computer according to a method of the invention to measure auditory area (residual hearing) of the patient and calculate filter parameters for the hearing aid;

Fig. 8 is a diagram of a table set up in a memory of the host computer for organizing sound pressure level data

10   indexed according to patient response and frequency range;

Fig. 9 is a graph of sound pressure level in decibels versus frequency, for use in predicting the performance of the hearing aid in mapping conversational speech onto the auditory area of the patient;

15   Fig. 10 is a flow diagram of operations of the host computer according to a method of the invention to monitor the operation of a hearing aid of the invention on the patient and to measure the resulting intelligibility of speech to the patient;

20   Fig. 11 is a flow diagram of operations of the host computer according to a method of the invention for inter-active, or adaptive, fine adjustment of the performance of a hearing aid of the invention;

Fig. 12 is a flow diagram of operations of a hearing

25 aid according to the invention for loading and executing entire programs;

Fig. 13 is a map of memory space in a hearing aid according to the invention;

Fig. 14 is a flow diagram of operations of a hearing

30 aid according to the invention for self-generating an output to cause test sounds to be emitted from the hearing aid into the ear of the patient;

Fig. 15 is a flow diagram of operations of a hearing aid according to the invention for reporting prestored cali-

35 brations to the host computer;

9

Fig. 16 is a flow diagram of operations of a hearing aid according to the invention for supplying the host computer with data for use in determining the sound pressure level in the ear canal;

5   Fig. 17 is a flow diagram of operations of a hearing aid according to the invention for implementing a self-adjusting filter-limit-filter digital filter; and

Fig. 18 is a flow diagram of operations of a hearing aid according to the invention for supplying the host computer
10 with data for use in determining sound pressure level in the ear canal and in monitoring the self-adjusting and limiting operations of the digital filter of Fig. 17.

Corresponding reference characters indicate corresponding parts throughout the several views of the drawings.

15 <u>Detailed Description of the Preferred Embodiments</u>

In the preferred embodiments one model of hearing aid can be programmed to fit virtually all hearing impairments. The hearing aid used in the hearing test can be the aid worn home by the patient. Consequently, delay in the
20 clinic between the traditional steps of initially testing the patient to specify the characteristics of the hearing aid and later retesting the patient with the representative finally-selected aid are eliminated. Also, because the hearing aid of a preferred embodiment includes a probe microphone, it is pos-
25 sible to measure the sound pressure in the ear both during testing and in normal use of the instrument. With the probe microphone in the hearing aid, testing and calibration are simplified, measurement of sound pressure in the ear is more accurate, and the overall input sound pressure to output sound
30 pressure characteristics of the aid can be controlled more exactly in normal use. Furthermore, with digital processing

10

techniques it is possible to adjust, more precisely, the gain
and maximum power output functions on a frequency-selective
basis.

5   The initial setting of the hearing aid parameters is
done automatically by a host computer that is preferably pro-
grammed to use certain fitting rules which offer maximum
speech intelligibility and comfort for the patient. These
rules of fitting are: 1) amplification of conversational
speech on a frequency-selective basis to fall within the
10   listener's range of comfortable loudness levels between 200
Hertz and 6000 Hertz, and 2) control of the maximum output on
a frequency-selective basis to fall below the listener's
uncomfortable listening level over the same range of frequen-
cies. A supplementary rule is that instrumentation noise and
15.   low-level background acoustic noise should fall below the
listener's threshold if possible.

         After the initial parameters have been determined, a
fine tuning of the "fit" can be achieved with an adaptive pro-
cedure made possible by the programmable nature of the aid to
20   reach an optimal setting. With the clinician operating the
host computer, the patient makes rapid comparisons of speech
intelligibility and comfort for various amplification charac-
teristics until a satisfactory fit is achieved. In such a
procedure, known as a paired-comparison procedure, the patient
25   is asked to make "better" or "worse" judgments in a manner
similar to that used in eyeglasses fitting procedures.

         In the above-described hearing aid fitting pro-
cedure, instrument characteristics of the earmold and trans-
ducers are advantageously taken into account during the hear-
30   ing aid evaluation. The hearing aid is worn by the patient
during the test so that the acoustic characteristics of the
hearing aid and earmold are included in the fitting procedure.
Significant fitting errors that heretofore have arisen due to
assumptions about calibration with standard test cavities
35   (roughly simulating the ear canal) are eliminated.

11

During the test, the hearing aid is connected to the
signal supplying apparatus, which has a host computer, via a
serial communication data link that mediates the transfer of
bidirectional digital signals consisting of signals for con-
5 trolling test sounds, signals representing measurement data,
and signals to program the hearing aid with appropriate signal
processing characteristics. At the completion of the test,
the hearing aid characteristics are optimized for the patient,
the serial communication data link is disconnected, and the
10 aid becomes a self-contained, self-adjusting unit that is worn
home by the patient. Fewer clinical visits are required with
concomitant advantages for the patient, clinician, employer
and community.

Such data as are needed to regenerate a copy of the
15 program for the hearing aid are archived by the host computer.
If and when the hearing aid needs to be replaced, another
hearing aid instrument is swiftly programmed with a regener-
ated copy of the program of the first aid modified in accor-
dance with the calibration data of the replacement aid. In
20 this way, the prior problems in hearing aid replacement are
avoided.

In Fig. 1, a clinical test system 10 automatically
controls the characteristics of a hearing aid 12 and generates
stimulus sounds and sequences used in testing the patient's
25 hearing. The system 10 has a small computer 14, herein also
called a "host computer." Host computer 14 has an associated
terminal 16, including a cathode ray tube (CRT) 18 and a key-
board 20 communicating through a serial interface 22, using
conventional electronic technique. Host computer 14 communi-
30 cates on a system bus 24 with flexible disk mass data storage
unit 26, a high-capacity hard disk data storage unit 28, and a
printer/plotter 30. Host computer 14 programs hearing aid 12
and receives measurement data back from it by means of a data
link 32 and a serial interface 34.

12

The host computer 14 also communicates with an
audiological testing subsystem (ATS) 36, which includes a
digital-to-analog converter (DAC) 38, signal attenuator 40, a
signal amplifying device such as a high-fidelity power ampli-
5 fier 42, and a loudspeaker 44. At the election of the clini-
cian operator at terminal 16, host computer 14 either disables
ATS 36, or causes ATS 36 to emit test sounds from loudspeaker
44 from a repertoire including tones, narrow band noise,
samples of speech, and other stored sounds. The repertoire is
10 illustratively stored on disk 26 or 28. ATS 36 constitutes
means controlled by an initiating or generating means (e.g.,
host computer 14), for selectively producing hearing test
sounds in the vicinity of hearing aid 12. ATS 36 is thus an
acoustic source for providing hearing test sounds to the
15 external microphone of the hearing aid 12 and is controlled by
the host computer 14.

An interactive response unit (IRU) 46 is provided
for the patient to use in registering responses to the sounds
heard through hearing aid 12 during the test. The IRU 46
20 senses the patient's responses and digitally communicates the
response data back to host computer 14 through a serial inter-
face 48. IRU 46 can be three push-button switches correspond-
ing to barely audible sound, comfortable sound, and uncomfort-
ably loud sound. However, greater flexibility is achieved
25 with a touch-screen video unit for IRU 46 in which host com-
puter 14 can display patient response instructions and choices
on the screen. Then the patient touches a display choice area
on the screen to register a response to sound. IRU 46 in a
third form is implemented as a terminal unit identical to
30 terminal 16, and the patient enters responses through a key-
board thereof.

In Fig. 2, hearing aid 12 has an electronics module
61, an earhook cable assembly 63, and a transducer module 65
retained within an ear mold 67 for insertion into the ear of

13

the patient. Earhook cable assembly 63 includes a flexible
plastic tapered tube 63A surrounding a cable 63B having six
fine insulated conductors terminated at a miniature connector
64 that plugs into the electronics module 61 worn behind the
5   ear. The earhook cable assembly 63 can be manufactured in
several different lengths to accomodate different sizes of
ears. Data link 32 attaches to electronics module 61 by means
of a connector 69 and provides temporary power to the hearing
aid as well as serving as a communications medium. When the
10   testing is completed, connector 69 and data link 32 are
removed from the hearing aid 12, and a rechargeable battery
pack 71 is snapped in place against electronics module 61 for
powering the hearing aid in normal use.

         In Fig. 3, the transducer module 65 has a plastic
15   casing 73 containing a microphone 75 mounted for receiving
external sound. Microphone 75 is called an "external micro-
phone" herein because it receives external sound, even though,
as shown, it is not physically external to the hearing aid
12. Sound enters the hearing aid at a port 76 positioned in
20   the transducer module 65 to take advantage of the acoustic
amplification and directivity of the external ear. Casing 73
also contains a second microphone 77, which is called a "probe
microphone" herein because it receives sound from the ear
canal.

25   Further contained in the casing 73 is a composite
receiver constituted by a woofer 79 and a tweeter 81. A
"receiver" as the term is used in the hearing aid art is not a
microphone, but a sound emitting means analogous in function
to a telephone receiver. (The hearing aid receiver is gen-
30   erally different in construction and much smaller than a tele-
phone receiver.) Woofer 79 is an electrically driven device
for emitting sound into the ear of the user of the hearing aid
12 in a low frequency range, and tweeter 81 is similar except
that it emits sound in a high frequency range. Together, they

14

are able to cover the entire spectrum of nominally 200 to 6000 Hz. with sufficient fidelity to accomodate the hearing needs of the hearing impaired patient.

5   Thus, external microphone 75 constitutes a microphone for generating an electrical output from sounds external to a user of the hearing aid, and woofer 79 and tweeter 81 constitute an electrically driven receiver for emitting sound into the ear of the user of the hearing aid. Transducer module 65 constitutes a body adapted to be placed in communi-
10   cation with an ear canal, the hearing aid body having an external microphone sensitive to external sound, a receiver for supplying sound to the ear canal, and a probe microphone for sensing the sound present in the ear canal. The electrical drive for the woofer and the tweeter is separated into
15   high and low frequency ranges. The separation feature reduces processing noise and improves dynamic range. As such, the receiver comprises a plurality of transducers driven by a driving means in distinct frequency ranges respectively.

Probe microphone 77, woofer 79 and tweeter 81 are
20   acoustically connected by respective sound tubes 83, 85, and 87 to the ear canal, when the hearing aid is in place. The sound tubes form a bundle having an outside diameter of approximately 5 millimeters or less, oriented at 45° toward the center line of the head of the patient. The sound tube
25   for the probe microphone 77 has an approximately 1.5 milli- meter inside diameter and is about 24 millimeters long.

As shown in Fig. 3A as well as Fig. 3, ear mold 67 is a soft molded plastic element that is inserted into the ear when the hearing aid is used. Ear mold 67 has one or more
30   channels admitting sound tubes 83, 85, and 87 to respective apertures 83', 85', and 87'.

External microphone 75, probe microphone 77, woofer 79, and tweeter 81 are acoustically isolated from each other in casing 73 by a cushioning foam material 89. Woofer 79 and

15

tweeter 81 are suspended in the material 89 while external
microphone 75 is affixed to casing 73. This provides an addi-
tional degree of acoustic isolation and freedom from feedback
squealing.

5   In Fig. 4, sounds are received at the external
microphone 75, such as a commercially available Knowles model
EA 1845 subminiature electret condenser microphone. This
microphone has wide bandwidth (150-8000 Hz.), smooth response
($\pm$5 dB), small volume (0.051 cc.), good electrical stability
10 and low sensitivity to vibration. External microphone 75 is
energized by lines to voltage V and ground, and produces an
electrical output on a line 101 connected to a signal condi-
tioning circuit 103.

          Signal conditioning circuit 103 applies a preempha-
15 sis, or "tilt", of 6 db per octave rising with frequency for
frequencies below 6 KHz., and then applies signal compression.
The signal compression is part of a companding approach in
which the compression is complemented with expanding in soft-
ware. Signal conditioning circuit 103 produces a preempha-
20 sized band limited (anti-aliasing) and compressed output which
is converted into discrete digital samples by combined actions
of a multiplexer (MUX) 105, a sample-and-hold circuit (S/H-IN)
109 and an analog-to-digital converter (ADC) 111. The nominal
sampling rate for each channel of MUX 105 is 50 KHz.

25   Anti-aliasing filter of signal conditioning 103
relatively flat from 0 to 6 KHz. and drops off "fast" enough
(in dB per octave) to ensure that there is negligible spectral
energy above 25 KHz. Signal conditioning 103 should provide
about 5 volts output with 89 dB sound pressure level at the
30 microphone input. For an EA series microphone with sensi-
tivity of about -60 dB re 1 volt per microbar, voltage gain at
1 KHz should be about 60 dB. Above 6 KHz., to reduce the
effects of aliasing, the system response should roll off at
-30 dB per octave to assure an adequately low (-60 dB) signal
35 at the Nyquist rate of 25 KHz (12.5 KHz. per channel).

16

ADC 111 is connected to a digital signal processor
(DSP) 113 and is constructed with conventional electronic
technique to implement a 16-bit successive approximation con-
version procedure. This results in fast conversions to pro-
duce digitized samples with 16 bits of dynamic range and ade-
quate precision for small signals. When preemphasis and com-
pression are applied by use of the signal conditioning circuit
103, the signal-to-quantizing-noise ratio is increased to a
high level. Accordingly, it is contemplated that the skilled
worker will reduce the number of bits of conversion in the ADC
111 to a minimum (10 or even 8 bits) consistent with accept-
able level of signal-to-noise ratio, when the reduced com-
plexity in ADC 111 more than offsets in value the use of sig-
nal conditioning circuit 103 and expander software in DSP 113.

The digitized samples are processed by digital sig-
nal processor (DSP) 113, which consists of a flexible array of
electronic logic elements that can be programmed to self-
generate waveforms corresponding to test sounds, to provide an
extremely wide range of filter characteristics for the hearing
aid, to process and report data from the probe microphone, to
gather and report data on the filtering operations, and per-
form other functions. DSP 113, for example, is a 16 bit
microprocessor chip fabricated according to VLSI (very large
scale integration) to physically fit in electronics module
61. Associated with DSP 113 is a random access memory (RAM)
115 and read-only memory (ROM) 117.

In its filtering mode of operation, DSP 113 acts as
four contiguous 8th-order band-pass filters that extend over a
total range of frequencies from 200 to 6000 Hertz in four
bands 240-560 Hz., 627-1353 Hz., 1504-3412 Hz., and 3755-5545
Hz. The bands or ranges are respectively given range numbers
$F = 1, 2, 3$ and 4. DSP 113 is programmed in its filter mode
to execute digital filtering operations (described more fully
in connection with Fig. 17) in the four bands. Several

/7

alternative filtering algorithms can be used. These include both Infinite Impulse Response (IIR) and Finite Impulse Response (FIR) filters. DSP 113 is equally capable of performing any of the alternatives, and only the program needs to be changed to implement an alternate method. The IIR type is believed to produce somewhat greater roundoff noise compared to that produced by the FIR. Accordingly, the FIR is disclosed in the preferred embodiment due to its superior signal-to-noise ratio.

DSP 113 produces a succession of digital signals that are converted to analog form by a digital-to-analog converter (DAC) 119. The output from DAC 119 is a succession of analog levels representing the sum of the digital filter outputs in the lower frequency bands F=1 and 2, alternating with the sum of the digital filter outputs in the higher frequency bands (F=3 and 4). The output of DAC 119 is connected to first and second sample-and-hold circuits (S/H1 and S/H2) 121 and 123. Sample-and-hold circuits 121 and 123 are alternately enabled by DSP 113 through a decoder circuit 125 and a control latch 127 so that the analog levels for the lower frequency bands F=1 and 2 appear at the output of S/H1 and the analog levels for the higher higher frequency bands F=3 and 4 appear at the output of S/H2. In this way the analog levels are routed to separate higher and lower frequency output channels.

Each sample-and-hold circuit 121 and 123 is not allowed to sample the output of DAC 119 during the first half of the settling period of DAC 119. The reasoning is that the DAC 119 is alternately producing independent signals. This can cause many jumps in its output. These jumps are isolated from the sample-and-hold circuits 121 and 123, and thus from the ear of the patient, by waiting for DAC 119 to at least partially settle before enabling the sample-and-hold circuits.

At this point it is useful to return briefly to the discussion of the advantage of two output channels. Either

18

output channel, in an example circuit operation with 8-bit digital representation, may produce an intense tone of 80 dB SPL with an audible quantization noise floor of 32 dB (i.e. a signal to noise ratio of 48 dB (6dB x 8 bits)). (Quantization

5   noise is produced by the digitizing process.) Due to the attenuation of out of band frequencies provided by the woofer and tweeter the quantization noise is suppressed well below that achievable with a single receiver design.

Woofer 79 and tweeter 81 are respectively fed by

10   S/H1 and S/H2 through coupling capacitors 129 and 131 respectively. Woofer 79 and tweeter 81 are commercially available Knowles model CI-1955 and EF-1925 units. Woofer 79 responds to low frequency signals below about 1500 Hz. (to encompass frequency bands F=1 and 2), and tweeter 81 responds to signals

15   above about 1500 Hz. (frequency bands F=3 and 4). The response of a Knowles tweeter can be made very low below frequencies of 1500 Hz. by drilling a very small hole (less than 1 mm.) in the case of the receiver itself to couple by an acoustic mass the front and rear of the diaphragm. At low

20   frequencies where the mass reactance is low, most of the volume velocity that otherwise is directed out of the sound port is advantageously shunted to the rear of the diaphragm.

It is contemplated that woofer 79 and tweeter 81 together with the natural filtering characteristics of the ear

25   will provide a significant and adequate degree of anti-aliasing filtering for the output channels. However, filtering, and power gain can be added in the lower and higher frequency output channels by optional anti-aliasing filters 133 and 135. When preemphasis is applied in signal conditioning

30   circuit 103, deemphasis is applied in the filters 133 and 135. (Deemphasis can alternatively be programmed into the digital filter software of DSP 113 if it is desired to omit the analog filtering.) Small push-pull amplifiers manufactured by Linear Technology or Texas Instruments can be used to supply the

35   power gain for exciting the woofer/tweeter combination.

/9

The probe microphone 77, such as a commercially available Knowles EA 1934 subminiature electret condenser microphone, is connected by a line 141 to a signal conditioning circuit 107. Signal conditioning circuit 107 applies a

5   gain of about 8 dB and optionally compresses the signal from the probe microphone output 141 to provide a second input to multiplexer 105. Probe microphone 77 constitutes a second microphone adapted for sensing sound in the ear of the user of the hearing aid. DSP 113 receives a succession of digital

10   signals from ADC 111 representing values of conditioned output from the external microphone 75 alternating with values of output from the probe microphone 77. DSP 113 through the decoder circuit 125 and the control latch 127 sequentially enables MUX 105 for the external microphone, enables S/H-IN

15   109, and then ADC 111. After the just mentioned sequence, DSP 113 sequentially enables MUX 105 for the probe microphone, enables S/H-IN 109, and then ADC 111. In the embodiment of Fig. 4 the output from the probe microphone bypasses signal conditioning circuit 103 and does not receive preemphasis, to

20   avoid complications in interpreting the output of ADC 111 for the probe channel. In this way, the analog levels representing the values of signal from the external microphone and from the probe microphone are multiplexed and converted to corresponding digital representations fed to DSP 113.

25   Thus MUX 105 has respective inputs for coupling to the probe microphone 77 and to the external microphone 75, and the output of MUX 105 is coupled to DSP 113 by way of S/H-IN 109 and ADC 111. Signal conditioning circuit 103 constitutes means for coupling the output of the external microphone with

30   preemphasis or compression or both, to one of the inputs of MUX 105. Signal conditioning circuit 103 applies the preemphasis and/or compression to the output of the external microphone, and the probe microphone is connected via signal conditioning circuit 107 to MUX 105 so as to bypass the preemphasis

35   means (e.g., circuit 103).

20

DSP 113 is a processor with sufficiently fast hard-
ware and software to complete its input, computation, and out-
put operations in about 80 microseconds (reciprocal of sampl-
ing rate of 12.5 KHz.) for each of many loops. The dynamic
5 range and signal-to-noise ratio are improved by the use of
16-bit digital representations, so a 16-bit processor is pre-
ferred. A Texas Instruments TMS-320 microprocessor or its
equivalent is a suitable choice for DSP 113.

The TMS-320 has a data area contained within while a
10 program area is connected externally. The data memory is 144
words by 16 bits and the program memory is 4096 x 16. The
program memory is separated into the ROM area 117 and the RAM
area 115. The ROM area contains the monitor program for DSP
113 (see Fig. 12), while the RAM area is loaded by the monitor
15 (see Fig. 13). In the practice of the invention the skilled
worker should increase or decrease the nominal 4K of memory to
the minimum memory required to accommodate the operations
implemented, or including those likely to be implemented in
the forseeable future.

20   There are eight I/O ports associated with the
TMS-320, which are available for local peripherals. The
skilled worker may make any appropriate port assignment for a
serial interface 151, ADC Register 111A, control latch 127 and
DAC Register 119A.

25   The TMS-320 utilizes programmed input-output (I/O)
with an I/O space of 8 words. I/O cycles and memory cycles
are for the most part identical, the biggest difference stem-
ming from the fact that the TMS-320 overlaps instruction and
data fetches. Since all data fetches are internal to the
30 TMS-320, these are done concurrently with the instruction
fetch for the next cycle. This means that, although data is
transferred in the same amount of time for memory references
and I/O references, I/O references can only occur every other
cycle because the IN or OUT instruction must be fetched over
35 the same bus on which the I/O transfer will take place.

21

An entire bus cycle of 'the TMS-320 is about 200 nanoseconds. RAM 115 and ROM 117 should have access times around 90 nanoseconds for use with the TMS-320. A 2K x 8 static complementary metal oxide semiconductor (CMOS) RAM of

5   type IDT6116S is a compatible chip for use as a memory build- ing block. To accomplish quick decoding, the memory is di- vided as simply as possible (halves or quarters), with the RAM 115 being enabled for the higher-numbered words and the ROM 117 for the lower-numbered words.

10   The interrupt (INT) line on the DSP 113 is activated whenever a character is received from host computer 14 of Fig. 1 through the serial interface 151. DSP 113 also enables the serial interface 151 through decoder 125 and a 2 line control bus 153. Serial interface 151 is an asynchronous serial port

15   which operates at programmable data rates up to 9600 baud and is of a readily available and conventional type. DSP 113 receives and sends information on a data bus 155 to serial interface 151, when the latter is enabled. In this way DSP 113 accomplishes two way serial communication with host com-

20   puter 14 of Fig. 1 along data link 32.

        The host computer 14 of Fig. 1 downloads programs and filter coefficients to the hearing aid 12 via serial interface 151. DSP 113 receives these programs and executes them. The serial data link to the host provides an effective

25   means of monitoring the status of the hearing aid 12. Status information that can be reported to the host computer includes: probe microphone sound pressure level measurements, extent of clipping in the multiband filters, and power spectra of input signals or filter outputs.

22

Bus lines marked 155 are, for purposes of clarity in illustration, shown emanating from DSP 113 on the drawing to ADC Register 111A, to serial interface 151, to control latch 127 and to DAC Register 119A. These bus lines are all marked
5 with the same numeral 155 because they are all part of the same data bus of DSP 113. ADC Register 111A has a tristate output, and other conventional arrangements are made so that bus 155 can be used in the multipurpose manner shown. Bus 155 is the data lines of a main bus 175. Main bus 175 not only
10 has the data lines, but also address lines and control lines connected from DSP 113 to RAM 115 and ROM 117.

Data link 32 illustratively has four conductors 161, 162, 163 and 164 in a flexible cable. First and second conductors 161 and 162 therein carry transmissions in respective
15 opposite directions 167 and 169 through connector 69 between the serial interface 34 of host computer 14 of Fig. 1 and the serial interface 151 of DSP 113. Third conductor 163 carries a power supply voltage V_{EXT} derived from the conventional power supply (not shown) of the host computer 14 for temporary
20 use as the hearing aid supply voltage V when hearing testing is being performed. Fourth conductor 164 is the ground return for data link 32 and for supply voltage V_{EXT}.

Connector 69 constitutes at least one external connector for making a digital signal (e.g., measurement data
25 from probe microphone 77) externally available and for admitting additional digital signals so that the digital filtering means (e.g., DSP 113) can be programmed when the hearing aid is placed in communication with the ear canal.

The use of four conductors 161-164 in data link 32
30 allows for full duplex (simultaneous two-way) serial communication, and separates the DC supply conductor 163 from the information carrying conductors 161 and 162. Of course, as few as two conductors can be used if simplex (alternate one-way) serial communication is chosen, and components are

added in electronics module 61 according to conventional tech-
nique for separating the supply voltage V from the serial
digital signals on data link 32.

     Battery pack 71 is shown in Fig. 4 with battery con-
5   nections to two conductors 163' and 164' of a connector 69'.
No connections (NC) are made to two other conductors of the
connector 69'. When hearing testing is completed, the serial
data link 32 and connector 69 are disconnected from module 61
and replaced by connector 69' which is snapped into place to
10 provide supply voltage V. During the interval of disconnec-
tion, a tiny battery 167 maintains a voltage on volatile RAM
115 so that software which has been downloaded during the
hearing aid fitting procedure is not lost. The RAM 115 is
supplied with supply voltage V through diode 169 at all other
15 times. When supply voltage V is restored, the reset R pin of
DSP 113 is supplied with a pulse from a power-on reset (POR)
circuit 171 such as a one-shot multivibrator to restart
execution of a program.

     In one aspect of its operations, DSP 113 constitutes
20 means for driving the receiver in a self-generating mode acti-
vated by a first set of signals supplied externally of the
hearing aid to cause the receiver to emit sound having at
least one parameter controlled by the first set of externally
supplied signals and for then driving the receiver in a
25 filtering mode, activated by a second set of signals supplied
externally of the hearing aid, with the output of the external
microphone filtered according to filter parameters established
by the second set of the externally supplied signals. When
the probe microphone is used, DSP 113 also constitutes means
30 coupled to the second microphone for also supplying a signal
for external utilization, the signal representing the at least
one parameter of the sound controlled by the first set of
externally supplied signals. Connector 69 constitutes an
external connector for making available the signal for

24

external utilization from said driving means and for admitting the first and second sets of signals supplied externally of the hearing aid.

5   A small bootstrap monitor program resides in the ROM 117. The bootstrap monitor assists the host computer 14 of Fig. 1 in downloading selected programs from the host computer to the RAM 115 in just a few seconds. A typical downloading process entails the transmission of about 2K bytes of program to DSP 113 at a data rate of 9600 baud. This is completed in
10   about 2 seconds.

Once the DSP 113 program is loaded, new filter coefficients and limiting values can be transmitted in less than a second once they are determined or selected from store by host computer 14 of Fig. 1. To facilitate a paired comparison
·15 fitting procedure, several sets of coefficients are advantageously computed in advance, and then the hearing aid filter characteristics are completely respecified at one second intervals.

Once a program is loaded, execution commences, and
20   the hearing aid 12 is operational. Thus, DSP 113 also constitutes digital computing means in the hearing aid and coupled to the external microphone, to said probe microphone and to the receiver, and adapted for connection to the external source of programming signals, said digital computing means
25   comprising means for loading and executing entire programs represented by the signals and thereby utilizing said probe microphone, the external microphone and the receiver for hearing testing and digital filtering.

DSP 113 is also programmed to control the power
30   usage of various parts of the hearing aid to conserve battery life when input sound levels fall below a specified criterion.

In Fig. 5, operations of host computer 14 commence with START 201 and proceed to a step 203 displaying menu options entitled:

25

"1.   PATIENT INTERVIEW: UPDATE PATIENT DATABASE"

"2.   CALIBRATE FOR EAR IMPEDANCE"

"3.   MEASURE AUDITORY AREA AND CALCULATE FILTER PARAMETERS"

"4.   SPEECH INTELLIGIBILITY TEST"

5   "5.   INTERACTIVE FINE ADJUSTMENT"

         The operator of the host computer selects one of the
menu options, and in step 205 a branch is made to execute the
selected one of the options. Option 1 is usually to be
selected first and executed·at step 207, whence operations
10   return to step 203 so that another option can then be
selected. A selected one of options 2, 3, 4, and 5 is then
respectively executed at step 209, 211, 213, or 215.
         Patient interview step 207 is a standard interactive
database update routine wherein the computer flashes form
15   questions on the CRT 18 of Fig. 1 and the operator asks the
questions and enters the answers of the patient on keyboard 20
of Fig. 1. Host·computer 14 of Fig. 1 stores the answers in
the database either directly or after some intermediate pro-
cessing in a manner familiar to the art. Accordingly, no
20   further description of the database update routine is under-
taken here.
         Calibrating step 209 gathers preliminary data on the
hearing aid and its characteristics when inserted in the
patient's ear so that step 211 can be performed accurately.
25   Step 211 then uses the data gathered in step 209 together with
measurements of the auditory area (defining the patient's
hearing) to then automatically calculate filter parameters
which will make the hearing aid ameliorate the patient's hear-
ing deficiency. The hearing aid 12 is programmed to operate

26

in accordance with the automatically calculated filter parameters, so that further testing and fine tuning by the operator can be performed in steps 213 and 215 to make the fit as perfect as possible. It is contemplated that each menu option is

5   performed once, in 1 through 5 order, but it is noted that each of the options on the menu can be accessed more than once and in any order to fulfill any procedural preferences of the operator. Also, if desired, one or more of the options can be omitted at the discretion of the operator.

10   In Fig. 6, the calibration for ear impedance, step 209, is itself divided into steps. Before describing the steps hereinbelow, the preliminary data sought is now discussed. Designations of the data and symbols for other quantities of interest are shown in Table I.

15   TABLE I

     QUANTITY   REMARKS

     HE(F)   Magnitude of the transfer function of the
                  path from external sound source through
                  external microphone, to input of DSP 113

20   of Fig. 4 in frequency range numbered F

     HR(F)   Magnitude of the transfer function of the
                  path from DSP 113 of Fig. 4 output to stan-
                  dard coupler in frequency range numbered F

     HP(F).   Magnitude of the transfer function of the

25   path from ear canal through probe microphone
                  to input of DSP 113 of Fig. 4 in frequency
                  range numbered F

37

SC(F)		Magnitude of the compensation function required due to deviation of actual ear impedance from that of standard coupler at frequency F. (SC(F)(dB) = HR(F) measured on patient (dB) less HR(F) measured in test cavity (dB))

A   Root mean-square (RMS) magnitude of waveform represented by the output of DSP 113 of Fig. 4

SPL   RMS sound pressure level in ear canal

$\sqrt{M/N}_M$ RMS input to DSP 113 from probe channel

A transfer function for the present purposes is a set of complex numbers corresponding to a set of frequencies in the spectrum of interest. In the preferred embodiment, the spectrum from 0 to 6 KHz. is divided up into a plurality of frequency ranges given range numbers F from 1 to some counting number FO such as 4. More specifically, a transfer function is the ratio of the Fourier transform of the output at one point in a system to the Fourier transform of the input to another point in the system. For simplicity, the use of complex numbers is avoided herein by employing the magnitude of the transfer function, where the magnitude is a function of frequency, which function is defined as the square root of the sum of the squares of the real and imaginary parts of the transfer function at each frequency in the spectrum. It is also assumed that the magnitude of the transfer function in each one of the frequency ranges is substantially constant, so that computations are simplified. It is readily verified from a mathematical consideration of complex numbers that the magnitude of the transfer function is equal to the ratio of the root-mean-square of the output to the root-mean-square of the

28

input. Moreover, paths or channels between points can be cascaded. The magnitude of the transfer function for the cascaded paths is the product of the magnitudes of the transfer functions of the respective paths.

5   In hearing aid 12, the output channel from DSP 113 to the woofer/tweeter receiver combination and ending in the ear volume (volume of the ear canal with hearing aid inserted), is regarded as a first path. This first path is cascaded with a second path constituted by the probe channel
10   to DSP 113 from tube end 83' and including the probe microphone. Because facilities will not generally be available in the field to calibrate the receiver and the probe microphone, it is contemplated that factory calibration will be accomplished with a standard acoustic device called a "coupler" for
15   simulating the ear volume. In the factory calibration of the hearing aid with the standard coupler, electrical output from DSP 113 is produced corresponding to a desired test sound in one of the frequency ranges at a time. This electrical output has a RMS value designated A and frequency range number F both
20   of which can be predetermined or controlled from a host computer 14 at the factory. The value A is regarded as the input to the first path. The acoustic output from the first path, which is also the input to the second path at end 83' of the tube 83 to the probe microphone, is the RMS sound pressure
25   level SPL. The RMS output of the second path is designated $\sqrt{M/N_M}$ for reasons described more fully hereinafter.

Both A and $\sqrt{M/N_M}$ can be measured or determined at the factory. SPL is measured by standard acoustic test equipment connected to the coupler at the factory. The transfer
30   functions of the above-mentioned cascaded first and second paths are designated HR(F) and HP(F) respectively determined at the factory from the measured values of A, SPL, and $\sqrt{M/N_M}$ using the equations:

29

$$SPL(F) \quad = \quad HR(F) \times A \tag{1}$$

and $\quad \sqrt{M/N_M} \quad = \quad HP(F) \times SPL(F) \tag{2}$

Similarly, the function HE(F) is the frequency-dependent ratio of the DSP 113 RMS input to an RMS sound pres-
5   sure level supplied to the external microphone 75 from a standard sound source.

The functions HE(F), HR(F) and HP(F) determined at the factory are supplied on a data sheet sent with the hearing aid to the clinician in the field. In an even more advan-
10   tageous feature of the invention, the functions HE(F), HR(F) and HP(F) are also loaded into the hearing aid memory so that they can be automatically retrieved by the host computer, thereby saving time and avoiding possible errors in entering the values from the data sheet into the host computer prior to.
15   the fitting procedure.

It is to be understood that the acoustic charac-teristics of the ear volume of the patient will in general be different from those of the coupler used at the factory. Con-sequently, it is desirable to calibrate for the ear impedance
20   in the field. The modifying effect of the actual ear volume compared to the coupler is accounted for by a frequency-dependent compensation function SC(F) which is determined by the operations of the host computer shown in Fig. 6. (The term "compensation function" signifies a mathematical correc-
25   tion herein, and is not to be equated by itself with hearing deficiency "compensation", which is an overall goal of hearing aid fitting.)

In the calibration of the ear volume of Fig. 6, electrical output from DSP 113 is produced corresponding to a
30   desired test sound in one of the frequency ranges at a time. This electrical output has an RMS value designated A and fre-quency range number F both of which can be predetermined or

30

controlled from host computer 14. The value A is regarded as the input to the first path. The transfer functions of the above-mentioned cascaded first and second paths, with the patient's ear canal included, are designated (SC(F) x HR(F))
5   and HP(F) respectively. The acoustic output of the first path, which is also the input to the second path at aperture 83', is the RMS sound pressure level SPL. Accordingly, the cascaded paths are described by the equations:

$$\sqrt{M/N_M} \;=\; HP(F) \;\times\; SC(F) \;\times\; HR(F) \;\times\; A \tag{3}$$

10

$$SPL(F) \;=\; SC(F) \;\times\; HR(F) \;\times\; A \tag{4}$$

and $$\sqrt{M/N_M} \;=\; SPL(F) \;\times\; HP(F) \tag{5}$$

Since HP(F) is known, the $\sqrt{M/N_M}$ data obtainable from the probe microphone measurements can be used to determine the actual sound pressure level SPL(F) in the patient's
15   ear. The value of A can be predetermined by the host computer also. Accordingly, and since the transfer function HR(F) is also known, the scaling function can be and is determined by host computer 14 by solving Equations (4) and (5) for SC(F).

Operations in host computer 14 commence in Fig. 6
20   with BEGIN 225 and proceed to step 227 to download a routine REPORT1 (Fig. 15) into the hearing aid for causing DSP 113 to send back the values of the transfer functions HE(F), HR(F) and HP(F) in each of the FO=4 frequency ranges. Next, at step 229, host computer 14 inputs and stores the values being sent
25   back from the hearing aid. In step 231, a stimulus generator routine (Fig. 14) including a routine called REPORT 2 (Fig. 16) is downloaded from host computer 14 to the hearing aid. Thus, host computer 14 downloads an entire test sound generating program to the hearing aid as a first set of signals.
30   In step 233 a test frequency in one of the frequency ranges

31

and a desired value of A are selected by the operator so that the test sounds produced have a comfortable loudness level for the patient while the ear impedance calibration test is being performed. Coefficients for the stimulus generator routine

5   are sent in step 235 to the hearing aid so that a test sound in the selected frequency range is emitted by the hearing aid into the patient's ear.

In step 237, host computer 14 receives a value M of sum-of-squares input in the probe channel of the hearing aid

10   12 from DSP 113 via REPORT 2. The value M is then divided by N_M in the host computer 14 and the square root of this value is calculated to obtain an RMS value $\sqrt{M/N_M}$ which is divided by the value of probe microphone transfer function HP(F) for the value of F of the frequency range in which the test sound

15   was generated. The result of the calculations is a value of measured sound pressure level SPL which is then stored in a table indexed according to frequency range in which the SPL measurement was taken.

At step 239 a branch back to step 233 is made to

20   test sounds in all four frequency ranges. When data has been gathered, scaling step 241 is reached. In each frequency range F, the compensation function SC(F) is calculated in each frequency range F according to the formula:

$$SC(F) \quad = \quad SPL(F)/(HR(F) \times A) \qquad\qquad (6)$$

25   where SPL(F) is the value in the SPL table corresponding to a given frequency range, HR(F) is the transfer function of the output channel in the hearing aid, and A is the RMS DSP 113 output used in producing the SPL(F). It is to be understood that the formula shown for step 241 is to be calculated four

30   times so that all values of F are exhausted, a loop being omitted from the drawing for conciseness. Of course more than one value of SPL can be measured in each frequency range, and

32

more than one value of A can be employed. In such case, all
the data are accordingly tabulated in memory and indexed
according to frequency. Then more than one value of
SPL(F)/(HR(F)xA) is computed in each frequency range, and the
5   resulting quantities averaged to produce a single calculated
value of SC(F) in each frequency range. Upon completion of
step 241, RETURN 243 is reached and operations return to step
203 of Fig. 5.

        In Fig. 7 the auditory area routine 211 of Fig. 5
10 commences with BEGIN 261 and proceeds in step 263 to download
a digital filter program into the hearing aid 12. The digital
filter includes four frequency ranges or passbands. The gains
in the frequency ranges are made equal to each other, and no
limiting is introduced, which produces an overall flat fre-
15 quency response over the spectrum 0-6 KHz. The digital filter
has the routine called REPORT2 (Fig. 16) for sending back
measurement data from the probe microphone.

        In step 265, host computer 14 outputs patient
response graphics indicating different areas of the touch
20 sensitive screen of IRU 46 which can be touched by the patient
in response to the test sounds. The response choices shown on
the screen are:

        A.   TOO LOUD

        B.   LOUD

25   C.   GOOD

        D.   SOFT

        E.   BARELY AUDIBLE

        The patient is asked to listen for test sounds and
when one is heard, to touch the screen of the IRU 46 to indi-
30 cate the response chosen. In step 267, host computer 14
causes ATS 36 to produce a selected test sound in a series of
sounds varying in loudness and frequency. The sounds can be
produced through the hearing aid 12 itself as in Fig. 6, but
it is believed to be preferable to use ATS 36 for auditory

33

area measurements so that head diffraction and other effects
associated with actual use of the hearing aid are present. At
step 269, the IRU 46 is accessed for the patient response, and
in step 271 the host computer checks to determine whether a
5   response has been received. If not, a branch is made to step
273 where a timer is checked, and if a preset interval has not
yet elapsed, a branch is made from step 273 to step 269 whence
the IRU 46 is accessed again. If there is no response, and
time is up, a branch is made from step 273 to step 267 so that
10 a different amplitude or frequency or both are selected and a
new test signal is presented. When and if there is a response
during the preset interval, a branch is made from step 271 to
step 275 to receive sum-of-squares value M from hearing aid 12.

          In performing either the pair of steps 263 and 267,
15 or the pair of steps 231 and 233 of Fig. 6, the electronic
circuitry in the aid is caused to act as programmable digital
filter means for programmably producing perturbations having a
controlled electrical parameter (e.g., amplitude A) in
response to a first set of externally supplied signals from
20 the host computer (e.g., filter program), the sound emitted by
the receiver having a controlled parameter (e.g., sound pres-
sure level) corresponding to the controlled electrical parame-
ter of the perturbations. "Perturbations" is a general term
which includes waveforms generally, such as sine waves, noise,
25 and speech waveforms.

          In step 275, host computer 14 indexes and stores the
latest information received from the hearing aid and from IRU
46 in a sound pressure level table SPL. The SPL table is
indexed as illustrated in Fig. 8 according to the five
30 responses A, B, C, D, and E and according to frequency in a
discrete number R of frequency ranges which can be in general
more numerous than the digital filter ranges FO. Each cell in
the SPL table represents a set of memory locations for holding
respective sound pressure level data in the ear which was

34

measured in the same frequency range and received the same patient response.

Each calculated value of SPL is initially computed as the ratio $\sqrt{M/N_M}$ /HP(F) as discussed in connection with
5   step 237 of Fig. 6. By contrast with step 237, however, the calculated value is then converted to decibels by computing the common logarithm multiplied by 20. In a further contrast, each decibel value of SPL is stored in the table which is indexed according to patient response A-E, as well as
10 frequency range F.

In step 277, a branch is made back to step 267 to present the next test sound by means of ATS 36 unless sufficient data has been gathered, whence the test is terminated and operations proceed to step 279.

15 In step 279, host computer 14 calculates values, in each of the frequency ranges (equal in number to R), of uncomfortable loudness level (UCL(F)), most comfortable loudness level (MCL(F)) and hearing threshold (THR(F)) using the decibel data stored in the SPL table. UCL(F) represents the level
20 in each frequency range where sounds make the transition from being loud (response B) to too loud (response A). UCL(F) is computed in one simple procedure by simply sorting to obtain the smallest SPL value in the A cell in each frequency range. In an alternative and more complex procedure the values in the
25 loud and too loud categories A and B are compared to estimate where loud leaves off and too loud begins.

Most comfortable loudness level MCL(F) is computed for instance by taking the arithmetic average, or mean, of the values in each cell corresponding to response C (GOOD) in each
30 frequency range. Hearing threshold THR(F) is computed by computing the arithmetic average, or mean, of the values in each cell corresponding to response E (BARELY AUDIBLE) in each frequency range. Even when data in response categories B and D are not used in the calculations, the provision of categories

.95

B and D causes the patient to more effectively define which data belong in categories A, C, and E.

As shown in Fig. 9, the computation of UCL(F), MCL(F), and THR(F) delineates the auditory area of the patient in SPL in dB versus log frequency. Next, it is desired to fit a known spectrum of conversational speech to the auditory area so that the patient's hearing deficiency can be fully compensated or at least ameliorated. In step 281, digital filter parameters of gain G1(F) and G2(F) and limiting L(F) are computed to accomplish the desired fit. The resulting digital filter (Fig. 17) is downloaded to the hearing aid 12 with a reporting routine REPORT3 (Fig. 18) including a self-adjusting gain feature. In performing steps 269, 275, 279, and 281, host computer 14 obtains data representing the responses of the patient from the sensing means (e.g., IRU 46) and utilizes the response data in determining the second set of signals (e.g., digital filter to download).

The operations accomplished in step 281 utilize available experimental data on conversational speech. Conversational speech has been analyzed and found to have a mean value in decibels (here designated SM(F)) which varies with frequency. Most of the loudness variation, suggested by shaded area 282 of Fig. 9, in conversational speech is bounded by a curve 282A which is 12 dB above SM(F) and a curve 282B which is 18 dB below SM(F). To fit the speech to the auditory area of the patient, the gain of hearing aid 12 is set as a function of frequency to translate SM(F) to the most comfortable loudness level MCL(F). The digital filter in hearing aid 12 is provided with an initial gain G1(F) (dB) followed by limiting to a level L(F) (dB) followed by post-filtering gain G2(F) (dB).

In order to effectively utilize the dynamic range of the digital system consisting of the ADC 111, DSP 113 and DAC 119 the values of the initial and postfiltering gains G1(F)

36

and G2(F) are calculated to ensure that the limit value L(F) is conveniently equal to the largest number that can be produced by DSP 113 (7FFF in hexadecimal form is the largest positive number expressible in fixed point form by a 16-bit computer). By setting L(F) to this constant where

$$L(F) = 2^{B-1} - 1 \tag{7}$$

for a B-bit representation, the RMS values of the limited signals L(F) are all equal to L(F)(dB) - 3 dB where the quantity 3dB is subtracted to adjust from the peak value L(F) to the RMS for a sine wave.

Now the gain parameter G2(F) can be calculated. G2(F) is set so that a limiter output of L(F)(dB) - 3 dB will produce an SPL in the ear equal to the UCL(F). The signal path from the output of the limiter to the ear includes G2(F), SC(F) and HR(F). Hence

$$G2(F)(dB) = UCL(F)(dB) - [L(F)(dB) - 3dB]$$
$$- SC(F)(dB) - HR(F)(dB) \tag{8}$$

Equation (8) states that the postlimiting gain in dB is the difference between the patient's UCL curve and the limiting level for hearing aid 12. If the limiting level exceeds the UCL, then the postlimiting "gain" in dB is an attenuation.

It remains to obtain gain G1(F). As discussed above, the intelligibility of speech is most likely to be maximized, to the extent that _a priori_ calculations can do so, by also translating the average level of conversational speech SM(F) to the patient's most comfortable loudness level MCL(F). The average level SM(F) over the frequency spectrum is obtained from experimental analysis results such as those reported in "Statistical Measurements on Conversational Speech" by H.K. Dunn et al., _J. Acoustical Soc. of America_, Vol. 11, Jan. 1940, pp. 278-288. Since the most comfortable

37

loudness level is below the UCL, the hearing aid output for
MCL is below the limiting level L(F)(dB). Without the
limiting, the hearing aid gain is G1(F)(dB) + G2(F)(dB).

5   The just-stated hearing aid gain is made equal to
the difference of MCL(F)(dB) less SM(F)(dB) corrected for the
transfer function HE(F) of the channel consisting of the
external microphone and the signal path through signal condi-
tioning circuit 103, MUX 105, S/H-IN, and ADC 111. A further
correction is also made for the output channel path defined by
10   the transfer function HR(F) x SC(F). Since gain G2(F) is now
calculated from Equation (8), gain G1(F) is obtained according
to the formula:

$$G1(F)(dB) = MCL(F)(dB) - SM(F)(dB)$$
$$-SC(F)(dB) - HR(F)(dB) - HE(F)(dB) - G2(F)(dB) \qquad (9)$$

15   The digital filter in hearing aid 12 is programmed
to utilize gain values in terms of voltage amplification or
attenuation. Accordingly, the gain values are converted from
decibels to voltage gain by the formulas:

$$G1(F) = 10^{[G1(F)(dB)/20]} \qquad (10A)$$

20   and $$G2(F) = 10^{[G2(F)(dB)/20]} \qquad (10B)$$

The transfer functions HE(F), HR(F), and HP(F) are also in
terms of voltage amplification and are converted from dB to
voltage gain by:

$$HE(F) = 10^{[HE(F)(dB)/20]} \qquad (11A)$$

25   $$HR(F) = 10^{[HR(F)(dB)/20]} \qquad (11B)$$

$$SC(F) \quad = \quad 10^{[SC(F)(dB)/20]} \tag{11C}$$

$$\text{and} \quad HP(F) \quad = \quad 10^{[HP(F)(dB)/20]} \tag{11D}$$

In step 283, a standard quantity called the "Articulation Index" (AI) is calculated so as to predict the
5   quality of fit of the fitted hearing aid. Articulation Index is defined by ANSI Standard S3.5-1969 "American National Standard Methods for the Calculation of the Articulation Index." Calculations according to the standard are programmed into the host computer 14 and executed as step 283 utilizing
10   the auditory area information obtained in testing the patient.

In step 285 of Fig. 7 host computer 14 accomplishes display and recordkeeping functions associated with the measurement of the auditory area of the patient and the automatic calculation of filter parameters for hearing aid 12. A
15   graph of the auditory area with a spectrum of conversational speech fitted thereon (corresponding to Fig. 9) is displayed on the terminal 16 and, if elected by operator, put in hard copy form by means of printer-plotter 30. The display or printout also lists parameters of the hearing aid fitted to
20   the patient, such as the product of HR(F) x SC(F), the noise output of the hearing aid when no external sound occurs, and the articulation index AI. AI, limit function L(F), and gains G1(F) and G2(F) are stored in the patient data base along with the data entered in patient interview step 207 of Fig. 5,
25   whence RETURN 287 is reached.

Fig. 10 shows a flow diagram of operations for the speech intelligibility test operations of host computer 14. After BEGIN 291, an identification number ID of a list of test words is input in step 293 from the terminal 16. At step 295,
30   graphics for multiple choice word recognition responses by patient are output to IRU 46. In step 297, host computer 14 causes ATS 36 to play the next one of the test words on the

37

list for the patient with hearing aid 12 to listen to. Host
computer 14 in step 299 reads values reported back from the
hearing aid by the REPORT3 routine. The data values include a
constant CA, which is nominally 1.0, the changes in which
5   indicate changes in ear impedance. A set of data values
called FIRS(F) is a sum-of-squares output of DSP 113 for each
of the four frequency ranges of the digital filter. Another
set of data values called LIMCNT(F) indicates how many times
the speech waveform actually exceeded the limit function L(F)
10   in the digital filter.

In step 301, it is recognized that the LIMCNT(F)
values are being generated as each speech sample is actually
being played. Accordingly, values of LIMCNT(F) are summed or
otherwise processed over the entire speech sample so that a
15   total value indicating the amount of limiting on each sample
can be derived. In this way, the performance of the hearing
aid for particular words or other sounds can be observed and
subsequent fine adjustments facilitated.

In step 303, the patient response to the multiple
20   choice question on the IRU 46 is received from the IRU. The
data gathered from the hearing aid in step 299 and from the
IRU in step 303 are displayed to the operator on the terminal
16 in step 305. If it is desired to play more speech samples,
a branch is made from step 307 back to step 295 to continue
25   the test. If the test is done, then operations proceed to
step 309 to calculate the percent of the words which the
patient correctly recognized.

In step 311, the operator compares the articulation
index calculated for the hearing aid with the list ID, and
30   compares the predicted percent of correct answers based on AI
with the actual percent correct. At step 313, the values
displayed in step 311 are stored in the patient data base with
a complete record of the responses of the patient to each
question in the test, whence RETURN 315 is reached.

40

In a further set of advantageous operations shown in
Fig. 11, the operator of terminal 16 can adjust the filter
parameters programmed into the hearing aid 12 and calculate a
predicted performance of the hearing aid before deciding
5   whether or not to download the adjusted filter parameters.
Operations commence at BEGIN 321 and proceed to step 323 where
the operator enters one or more adjusted values of limit func-
tion L(F) and gains Gl(F) and G2(F) from terminal 16. In step
325, host computer 14 computes how the hearing aid would, if
10 programmed with the adjusted values, reposition the conversa-
tional speech spectrum 282 (Fig. 9) on the stationary auditory
area defined by the previously measured UCL(F), MCL(F), and
THR(F) curves. The articulation index is calculated according
to the above-cited ANSI standard from the foregoing informa-
15 tion in step 325. Then an informational display is fed to
terminal 16 showing the auditory area with the repositioned
conversational speech spectrum (hearing aid response curves),
and the value of the resulting AI. All of the adjusted and
unadjusted values of L(F), Gl(F), and G2(F) are also output
20 for operator reference.

At step 329, host computer 14 asks the operator
through terminal 16 for instructions. Operator inputs a
string designated A$. If A$ is "YES," operations branch back
from step 331 to step 323 and repeat steps 323 through 329 so
25 that the operator can further adjust values in an interactive
procedure in which the operator homes in on final filter
parameters for the hearing aid. If A$ is "LOAD," operator is
telling host computer 14 to proceed to step 333 to download
adjusted filter parameters to hearing aid 12 thus changing the
30 operation of the hearing aid itself to correspond to the
parameters adjusted by the operator. After step 333, the com-
puter 14 in step 335 stores the adjusted filter parameters
together with the most recently calculated value of AI in the
patient data base so that there is a record of this deliberate

4/1

change to the hearing aid. If in step 331, the string A$ is
"STOP," then the hearing aid is not changed, and RETURN 337 is
reached.

Thus, host computer 14 with its terminal 16 also
5   graphically displays hearing threshold, most comfortable loud-
ness level, uncomfortable loudness level, and performance
characteristics of the hearing aid (e.g., in mapping conversa-
tional speech onto the auditory area), and generates a third
set of signals (e.g., downloads an adjusted filter) determined
10 by interaction with an operator for establishing adjusted
filter parameters in the programmable filtering means.

DSP 113 loads and executes entire programs supplied
to it by host computer 14. Fig. 12 shows the download monitor
in DSP 113, "monitor" having its computer meaning of a
15 sequence of operations that supervise other operations of the
computer. Fig. 13 illustrates that the monitor is stored in
ROM 117 and a program having been downloaded is stored in RAM
115 beginning at an address ADR0, typically followed by data,
or coefficient space, followed by first executable contents at
20 an address ADR1 and the rest of the program in an area desig-
nated DSP Program Space.

The monitor of Fig. 12 is programmed as an interrupt
routine which commences at START 351, regardless of any other
program which may be previously running, whenever the inter-
25 rupt line INT is activated in Fig. 4. An index P is initial-
ized to zero in step 353. The monitor receives supervisory
information from the host computer 14 through serial interface
151 in step 355. The supervisory information is the numerical
value of the address to be used as ADR0, and the number of
30 bytes NR to be downloaded.

At step 357, DSP 113 inputs a byte of the program
and in step 359 stores that byte at a RAM address having the
value equal to the sum of the value of ADR0 plus the value of
the index P. Since P is initially zero, the first program

42

byte is stored at address ADR0. At step 361, index P is
incremented by one. Until P becomes equal to the number of
bytes NR, a branch is made at step 363 back to step 357 to
execute steps 357 through 361 again, thereby loading the
5   entire program being received from the host computer 14. When
P is the same as NR, step 365 is reached whence DSP 113 jumps
to ADR0 and begins executing the entire downloaded program
beginning with the contents of address ADR0.

         The monitor of Fig. 12 is uncomplicated and short,
10   which reduces the cost of programming ROM 117 at the factory.
The monitor is flexible in that it can be used to load a long
program into RAM and then subsequently write over a portion
such as the coefficient space, to change the parameters uti-
lized by the long program. Beginning address ADR0 can hold a
15   "jump" instruction to a different redefinable address ADR1,
adding further flexibility to the software. Because the
address ADR0 is defined by the host computer and can be rede-
fined, another program can be subsequently loaded starting at
a different value of ADR0 without having to reload a previous-
20   ly loaded program. Accordingly, improvements in hearing aid
12 can be accomplished by reprogramming from new editions of
software supplied for the host computer 14, thereby avoiding
burdening patients with the expense of a new hearing aid 12
itself.

25   Fig. 14 shows a stimulus generator routine down-
loaded into RAM 115 by means of the DSP 113 monitor of Fig. 12
and in response to the host computer step 231 of Fig. 6. The
stimulus generator is a set of DSP 113 operations for driving
the receiver of the hearing aid in a self-generating mode
30   activated by the signals which downloaded the stimulus gene-
rator. The stimulus generator routine essentially turns DSP
113 into an oscillator and a system for reporting back the
output of the probe microphone 77.

4/3

Operations commence at BEGIN 371. A set of variables J, N, and C are initialized at step 373 in which J is set to 2, N is set to 0, and C is set equal to a number precalculated in the host computer as 2 cos(2 x pi x f x delta-t). "pi" is 3.1416, the circumference of a circle divided by its diameter. "f" is the frequency of oscillation in Hertz (Hz.) selected by host computer 14. "delta-t" is a time interval between values generated by the stimulus generator. An amplitude parameter A is set to a value selected by the host computer. A table Y is indexed according to the variable J. Variable J is permitted to take on only three values 0, 1, and 2. Entry Y(0) is initialized to zero, and Y(1) is initialized to a number calculated in the host computer as sin(2 x pi x f x delta-t). A sum-of-squares accumulator M is initialized to zero.

In the discussion of Figs. 14 and 17 that follows, modulo notation is used for brevity. 0 modulo 3 is 0; 1 modulo 3 is 1, 2 modulo 3 is 2; 3 modulo 3 is 0, -1 modulo 3 is 2; -2 modulo 3 is 1, and -3 modulo 3 is 0. In general, X modulo B is X when X is greater than or equal to 0 and less than B. When X is greater than or equal to B, X modulo B is X-B for X less than 2B-1. When X is less than zero, X modulo B is X+B for X greater than -B-1. Modulo notation is useful in showing that only B memory locations in a computer are needed in a process that is progressing through memory locations indefinitely.

In step 375 of Fig. 14 an output value of a sine wave of amplitude 1 (RMS value of 0.707) is generated by calculating a value for the latest table entry $Y(J_{mod\ 3})$ in sequence as C times the next previous entry $Y((J-1)_{mod\ 3})$ less the entry $Y((J-2)_{mod\ 3})$. At step 377, the output of the stimulus generator is scaled up from the sine wave of amplitude 1 to produce an output value S by multiplying entry $Y(J_{mod\ 3})$ by the amplitude parameter A.

44

At step 379, DAC 119 of Fig. 4 is enabled by DSP
113, and the value of S is output in digital form from DSP 113
to DAC 119. DAC 119, of course, converts the value of S to
analog form. Then DSP 113 enables one and not the other of
5   sample-and-hold circuits 133 and 135 so that the analog output
is fed to one and not the other of woofer 79 and tweeter 81.
Step 379 is programmed to enable the correct sample-and-hold
circuit depending on the frequency f of the test sound being
generated. Such programming is readily accomplished because
10 frequency f is known a priori by host computer 14 when the
stimulus generator is downloaded for each test sound to be
generated.

At step 381, index J is incremented by one, modulo
3, to the value $(J+1)_{mod\ 3}$. At step 383, the report routine
15 REPORT2 is executed, sending back sum-of-squares information
gathered by probe microphone 77 to host computer 14. Depend-
ing on the speed of DSP 113 a preestablished waiting period is
programmed at step 385, so that when the operations proceed
back to step 375 to execute steps 375-383 again, the frequency
20 of the generated sound is at the predetermined frequency f.
It is to be understood that even though stimulus generator is
an endless loop with no RETURN or END, its operations are
interrupted and the monitor resumed simply by host computer 14
sending a character to interrupt DSP 113 and load the stimulus
25 generator routine with different frequency f, amplitude A, and
designation of SH1 or SH2.

A brief digression is made to describe the REPORT1
routine of Fig. 15. REPORT1 is downloaded from host computer
14 to DSP 113 in step 227 of Fig. 6. Its purpose is to obtain
30 the transfer functions HE(F), HR(F) and HP(F) which amount to
hearing aid calibration data and are prestored in the memory
of the hearing aid during manufacture. When the monitor
reaches step 365 of Fig. 12 after downloading REPORT1, it
jumps to BEGIN 391. REPORT1 proceeds to address, or enable,

the serial interface 151 at step 393. Next in step 395, the
values of HE(F), HP(F) and HR(F) for each value of F are
fetched from predetermined memory locations and transmitted
through serial interface 151 to host computer 14, whence END

5 397 is reached. In this way host computer 14, which is a
means for supplying REPORT1, also retrieves the calibration
data from the hearing aid memory and utilizes the calibration
data and a subsequently-obtained parameter of the probe micro-
phone output in determining and supplying the second set of

10 digital signals (e.g., a digital filter program).

The routine designated REPORT2 of Fig. 16 is incor-
porated as a subroutine in a downloaded program such as the
stimulus generator of Fig. 14 or the digital filter described
hereinafter in connection with Fig. 17. For example, in the

15 stimulus generator when step 381 is completed, operations pro-
ceed to BEGIN 401 of REPORT2 of Fig. 16. In step 403 of
REPORT2, the control latch 127 of Fig. 4 is addressed, or
enabled. In step 405 a sequence of bytes is supplied from
port P1 of DSP 113 to control latch 127, which successively

20 selects the probe microphone line 141 at MUX 105, enables
S/H-IN 109, then enables ADC 111, and finally senses a digital
representation S1 of the conditioned instantaneous voltage
from the probe microphone.

In step 407 the S1 value is squared and added to

25 accumulator variable M. Index N of step 373 is incremented by
1. At step 409, N is tested to determine if it has reached
N_M yet. If not, RETURN 411 is reached and no communication
to host computer 14 occurs yet. However, after N_M repeti-
tions of REPORT2, a branch is made from step 409 to step 413

30 at which the serial interface 151 is addressed and the value
of M is output to the host computer 14.

It should be understood that M is a sum-of-squares
and not a root-mean-square value. This, however, is no
problem, since the $N=N_M$ test at step 409 is known, and the

46

relatively time-consuming operations of division by N_M and
taking the square root of the result to obtain the actual
root-mean-square can be accomplished by host computer 14
(steps 237 and 275) where computer burden is not as important

5   as in DSP 113. The signal for M thus represents a mean-
square sound pressure parameter (e.g., square of SPL) by being
proportional thereto. After the value of M has been reported,
index N and accumulator variable M are reset to zero at step
415.

10   It is noted that the reference value N_M is a
prestored value which is set at 400 or to any other appropri-
ate value selected by the skilled worker. It is intended that
the sum-of-squares is to be accumulated in an appropriate and
effective manner to permit host computer 14 to obtain or

15 derive an RMS value for the probe channel which can be used to
accurately calculate sound pressure level SPL. Thus, errors
resulting from summing over only parts of cycles rather than
whole cycles should be avoided in programming the report
routine and host computer 14.

20   In this way the circuitry of Fig. 4 in performing
the operations described in Fig. 16 constitutes means coupled
to the second (probe) microphone for also supplying a signal
(e.g., M) for external utilization, the signal representing a
mean-square sound pressure parameter of the sound.

25   A flowchart of the digital filter routine for DSP
113 is shown in Fig. 17. When the monitor of Fig. 12 has
loaded the digital filter in response to step 263, 281, or 333
in the host computer, and completed step 363, operations com-
mence at BEGIN 421 and proceed to initialization step 423.

30 Indices N and N1 are set to zero, accumulator variables M and
M1 are set to zero, index I is set to 31, and a constant CA
(calculated in operations of Fig. 18) is set to one. A 32
element table S2(I) has all elements set to zero; and a
triplet of four-element output tables FIR(F), FIRS(F), and

47

LIMCNT(F) indexed by frequency range F respectively have all
elements set to zero. A 4-row, 32-column table LIM(I,F) is
initialized to zero. DAC 119 is initialized to zero to avoid
a transient in the receiver.

5   At step 425, REPORT2 (Fig. 16) is executed when the
digital filter is downloaded by step 263 of Fig. 7. Otherwise
REPORT3 (Fig. 18) is executed as a result of download step 281
or 333. At step 427, the frequency range index F is initial-
ized to 1, and a gain adjustment constant CA1 is derived as an
10 approximation to the reciprocal of the square root of constant ·
CA. (See discussion of REPORT3 for theory of CA1.). The con-
trol latch 127 is enabled in step 429. Step 431 represents a
sequence of operations for bringing in a sample from the
external microphone 75. Bytes supplied from port P1 enable
15 MUX 105 for the external microphone, then S/H-IN 109, then ADC
111, and finally sense a digital value. The digital value is
expanded, to offset the compression in signal conditioning
circuit 103, by applying an expansion formula or by table
lookup. The expanded value is then stored in location I of
20 table S2.

         The first gain step 433 of the digital filter is
executed according to a finite impulse response routine
expressed as

$$\text{FIR1} = G1(F) \times \overset{31}{\underset{J=0}{\text{SUM}}} [C_J(F) \times S2((I-J)_{\text{mod } 32})] \qquad (12)$$

The equation (12) of step 433 states that a linear combination
is formed by 32 prestored coefficients $C_J(F)$ with the 32
entries of the S2 table working backward modulo 32 in table S2
30 from the latest entry I. The linear combination, also called
convolution in the art, herein labeled as SUM, is multiplied
by a voltage gain G1(F) to produce the first output FIR1 ready
for limiting, if limiting be necessary. FIR1 is merely a

48

single word in the computer since it is computed and used immediately.

In step 435 limiting is performed so that the table LIM(I,F) is updated to have an entry at index I and frequency range F set equal to the lesser of FIR1 or L(F) when FIR1 is positive. LIM(I,F) is set equal to the greater of FIR1 or the negative of L(F) when FIR1 is negative. Thus, when limiting occurs, step 435 "clips" both the positive and negative peaks of the waveform presented to it. L(F) is simply the highest value, for example, of a word in DSP 113 (+7FFF for a 16-bit computer) or some other preselected binary value.

In step 437, a check is made to determine whether limiting took place, by comparing FIR1 with L(F). If FIR1 was excessive, then limiting-counter table LIMCNT(F) has the element for frequency range F incremented by one in step 439. Otherwise operations proceed directly to step 441.

At step 441 postlimiting filtering is performed. This step is analogous to step 433 in that the coefficients $C_J(F)$ are the same, but now it is the output of step 435 which is being filtered according to the formula

$$FIR2(F) = G2(F) \times \sum_{J=0}^{31} [C_J(F) \times LIM((I-J)_{\text{mod } 32}, F)] \quad (13)$$

where G2(F) is the postlimiting gain in frequency range F, and LIM is the 4 x 32 table for holding the output of step 435.

DSP 113 in performing steps 433, 435, and 441 constitutes programmable digital filter means for utilizing the filter parameters established by the second set of externally supplied signals (e.g., those downloading the filter) to establish the maximum power output of the hearing aid as a function of frequency. DSP 113 in performing steps 437 and 439 is caused to also supply or generate a signal for external

49

use in adjusting the performance of the hearing aid, the last-
said signal representing the number of times as a function of
frequency that the established maximum power output of the
hearing aid occurs in a predetermined period. There is a pre-
5   determined period because the accumulated values in LIMCNT(F)
are reported every N_M loops (see Fig. 18).

4-element table FIR2(F) has the element for
frequency range F updated by the computation of Equation
(13). Table FIR2(F) is a storage area so that after all of
10 the frequency ranges have been processed, the values in the
FIR2(F) table can be used almost simultaneously.

Next at step 445 a table FIR(F) accumulates the
sum-of-squares of FIR2(F) in each frequency range F for use in
connection with the self-adjusting feature hereinafter
15 described.

A test at step 447 determines whether all of the
frequency ranges have been filtered using the latest sample
S2(I). If F is less than 4, a branch is made to step 448 to
increment F and then do filter-limit-filter digital filtering
20 in the next higher frequency range. Finally F reaches 4, and
at step 449 a section of operations commences for forming the
output values to drive the woofer and tweeter respectively.

For purposes of determining the digital filter
characteristics (in-band ripple and out-of-band rejection),
25 the two steps 433 and 441 executed in any one frequency range
F are regarded as being the digital versions of two corre-
sponding analog filters. The two corresponding analog filters
are separate but illustratively identical analog filters hav-
ing four analog filter sections each. Each of the four analog
30 filter sections is defined by three specifying data: a tuning
frequency, a quality factor Q, and a gain A_o, which are set
forth as headings in Table II. Since there are four frequency
bands or ranges F=1, 2, 3, 4, in this preferred embodiment,
Table II shows values of the three specifying data for each of

50

the four analog filter sections in each of the four frequency
bands (a total of 16 analog filter sections).

TABLE II

	Band Edges (Hz)	Tuning Frequency (Hz)	Q	Ao	Filter Section
Low Filter	240 560	435 309 544 247	2.21 2.21 5.67 5.67	1.5 1.5 1.5 1.5	1 2 3 4
Low-Medium Filter	627 1353	1074 790 1318 644	2.44 2.44 6.20 6.20	1.5 1.5 1.5 1.5	1 2 3 4
High Medium Filter	1504 3412	2671 1921 3318 1546	2.29 2.29 5.86 5.86	1.5 1.5 1.5 1.5	1 2 3 4
High Filter	3755 5545	4921 4231 5467 3809	4.86 4.86 11.9 11.9	1.5 1.5 1.5 1.5	1 2 3 4

It should be noted that Table II defines the filters
without deemphasis. When digital deemphasis is desired, the
gain A_0 should be changed in Table II to provide the deem-
phasis. Otherwise, it is assumed that when preemphasis is
provided by signal conditioning circuit 103, corresponding
deemphasis is supplied by AAFs 133 and 135 of Fig. 4.

The coefficients $C_J(F)$ are precalculated and pre-
stored in the host computer 14 for each frequency range F to
implement in digital form the characteristics called for in
Table II. It is to be understood that there are 32 coeffi-
cients C_0, C_1, ..., C_{31} for each frequency range F=1, 2,
3, and 4. Consequently, there are a total of 128 (32x4) pre-

5/

stored $C_J(F)$ coefficients in the preferred embodiment
example of Fig. 17. The coefficients used in step 433 are
identical to those used in step 441 in this example. The pro-
cedure for precalculating the coefficients is known to those

5   skilled in the art and is disclosed for instance in "A Com-
puter Program for Designing Optimum FIR Linear Phase Digital
Filters" by J.H. McClellan et al., IEEE Transactions on Audio
and Electroacoustics, Vol. AU-21, No. 6, Dec., 1973, pp.
506-526.

10   In step 449, a DSP 113 output FIRA for the woofer
channel is formed as the product of gain adjustment constant
CA1 with the sum of the digital filter outputs FIR2(1) and
FIR2(2) in the two lower frequency ranges, where F=1 and 2.
At step 451 the woofer is fed the latest output value FIRA by

15   enabling the DAC 119, sending FIRA to the DAC 119 from DSP
113, and then enabling S/H1 to convert FIRA to analog form to
drive the woofer. Steps 453 and 455 are analogous to steps
449 and 451. In step 453 a DSP 113 output FIRB for the
tweeter channel is formed as the product of the gain adjust-

20   ment constant CA1 with the sum of the digital filter outputs
FIR2(3) and FIR2(4) in the two higher frequency ranges, where
F=3 and 4. At step 455, the tweeter is fed the latest output
value FIRB by enabling the DAC 119, sending FIRB to the DAC
119 from DSP 113, and then enabling S/H2 to convert FIRB to

25   analog form to drive the tweeter.

           At step 457, index I is incremented by one, modulo
32, and step 425 is reached. A report routine is executed and
then the next sample S2(I) from the external microphone is
digitally filtered. Then the woofer and tweeter are driven,

30   and so on repeatedly in an endless loop which is only termi-
nated by interrupting DSP 113. The endless loop is the con-
tinuous operation of hearing aid 12 in assisting the patient
to hear.

52

In connection with the operations of Fig. 17, advantageous techniques of digital signal processing are employed to reduce the processing load on DSP 113 wherever possible. For example, decimation and interpolation [Crochiere, R. E. and Rabiner, L. R., Optimum FIR Digital Filter Implementations for Decimation, Interpolation, and Narrow-band Filtering, IEEE Trans. Acoust. Speech, and Signal Proc., Vol. ASSP-23, pp. 444-456, October, 1975] are employed before and after the filter-limit-filter channels to reduce the computational sampling rate required of the filter-limit-filter calculation.

In the context of this preferred embodiment step 431 of Fig. 17 includes a low-pass filter of 6 kHz bandwidth followed by a 4 to 1 decimation (discard 3 out of 4 samples) of sampling rate from 50 kHz to 12.5 kHz. The filter-limit-filter calculations are then carried out at the reduced 12.5 kHz rate.

Included in steps 449 and 453 of Fig. 17 and before samples are output to the DAC 119 the sampling rate is increased from 12.5 kHz to 50 kHz through a process of interpolation of 1 to 4 (inserting 3 zeros between each sample) followed by low-pass digital filter with a cutoff of 1.5 kHz for the woofer output and a digital bandpass filter with lower and upper cutoff frequencies of 1.5 kHz and 6 kHz for the tweeter output.

The reporting routine REPORT3 in Fig. 18 is similar to REPORT2 (Fig. 16) except that REPORT3 additionally calculates constant CA for use in the self-adjusting gain feature. Accordingly, steps 461, 463, 465, 467, 469 and RETURN 471 are the same in nature and purpose to REPORT2 steps 401, 403, 405, 407, 409, and RETURN 411, so that further discussion of said steps is omitted for brevity. In REPORT3, however, when N reaches N_M, a branch is made to a step 473. At step 473, the serial interface 151 is enabled. DSP 113 communicates the

5̃3

values of accumulator variable M, a sum-of-squares filter out-
put table FIRS(F), constant CA, and limiting-counter table
LIMCNT(F) to the host computer 14 (used in step 299 of Fig.
10).

5   Step 475 reinitializes index N to zero and LIMCNT(F)
to zero for all F. However, for gain self-adjusting purposes,
index N1 is now incremented by one and another accumulator
variable M1 is incremented by M. Then at step 477, the first
accumulator variable M is reset to zero. At step 479 a branch
10   is made to RETURN 471 if N1 has not reached a prestored value
NM1 set at 500 or any other appropriate value.

        When N1 reaches NM1, which takes about 16 seconds
(typically 80 microseconds x 400 x 500), step 481 is reached,
wherein a calculation for self-adjustment of gain commences.
15   The ear impedance is a function of ear canal volume and other
factors. So long as the ear impedance remains the same as it
was when the procedure of Fig. 6 for calibrating was per-
formed, the value of constant CA should be unity. Step 481 is
performed after typically 200,000 (N_M x NM1) samples S1 from
20   the probe channel have been squared and summed to produce the
quantity M1.

        The quantity M1 can be regarded as being derived
from a single waveform having an 0-6KHz spectrum or from four
waveforms having spectra respectively covering each of the
25   digital filter frequency ranges. Because the four waveforms
are independent of each other, the sum M1 of the squares of
the single 0-6KHz waveform is equal to the total of the sum-
of-squares of each of the four waveforms if they were iso-
lated. This relationship is expressed mathematically as

30
$$M1 = \sum_{F=1}^{4} [FIR(F) \times HR^2(F) \times SC^2(F) \times HP^2(F)] \qquad (14)$$

54

M1 is the sum-of-squares of 200,000 samples of the output of ADC 111 to DSP 113 in the probe channel. FIR(F) is a sum-of-squares of 200,000 values of the waveforms in the four frequency ranges computed by DSP 113 in step 445. HR(F),
5   SC(F), and HP(F) are respectively the transfer function of the output channel, scaling constant to correct for the actual ear impedance, and the transfer function of the probe channel. They translate the waveforms in the four frequency ranges to the output of ADC 111. The right side of Equation (14) is a
10 prediction, therefore, of what M1 will be so long as the ear impedance of the patient does not change.

If the ear impedance does change, the actual measured M1 on the left side of Equation (14) will no longer be equal to the sum on the right side. This is because scaling
15 function SC(F) no longer describes the ear, as it has changed. Then as shown in step 481, constant CA is calculated as a function of the ratio of the right side of Equation (14) to M1.

It is noted that CA is calculated as a constant, i.e., a quantity independent of frequency, and not as a func-
20 tion of frequency range index F. This is because the calculation assumes that if the ear impedance does change, the correction should be equal in all frequency ranges or that such correction will cause a negligible departure from optimum fit. Moreover, the calculation of a single constant CA independent
25 of frequency keeps computer burden low and is thus preferred. Corrections can be made which are a a function of frequency, however, and such refinements are within the scope of the invention.

Step 481 is completed by limiting CA to a preestab-
30 lished range such as .5 to 2.0 (a ± 6 dB range). This is a precaution against unexpected values computed for CA which would be expected to only arise from causes other than a change in the ear impedance. Accordingly, if CA is computed to be a value in the range, that value is not modified by step

55

481. If CA is less than the lower limit, e.g. .5, then CA is set equal to the lower limit. If CA is more than the upper limit, e.g. 2.0, then CA is set equal to the upper limit.

In the Fig. 17 flow diagram at steps 427, 449, and
5   453, the value of CA resulting from step 481 of Fig. 18 is used, in effect, to adjust the postlimiting gain G2(F) by multiplying it by CA which is:

$$CA = 1 + a[(\sum_{F=1}^{4}(FIR(F) \times HR^2(F) \times SC^2(F) \times HP^2(F))) - M1] \quad (15)$$

where CA is limited to the range 0.5 to 2.0 and a is chosen to
10   control the sensitivity of CA to the difference enclosed in parenthesis. The reasoning behind the calculation of CA is based on Equations (7), (8) and (9). Constant CA is essentially a constant correction factor to SC(F) in each frequency range. Thus CA is a multiplying factor determined by a linear
15   approximation of the difference between the predicted and measured mean-square values. Equation (15) is an approximation to the square root of the ratio of the right side of Equation 14 to measured M1.

Equation (8) establishes a criterion that UCL(F) not
20   be exceeded by the preestablished maximum power output of the hearing aid. Gain G2 is therefore multiplied by a factor of CA, as shown in steps 449, and 453, when CA departs from unity. Equation (9) sets forth the relationship by which the speech mean SM is translated to the patient's MCL(F). Inspec-
25   tion of Equation (9) shows that it is also satisfied when CA departs from unity by applying CA as a factor as shown in Fig. 17.

Thus, the electronics module 61 as a driving means responds to the second (probe) microphone for also self-
30   adjusting the operation of the driving means in the filtering mode. The operations that produce CA in step 481 amount to comparing the output of the second microphone with the degree

56

of drive provided by the driving means to the receiver in the filtering mode. Applying CA amounts to self-adjusting at least one of the filter parameters (e.g., G2(F)) depending on the result of the comparison.

5   In step 483 of Fig. 18, the accumulated sum-of-squares FIR(F) information is stored in the storage table called FIRS(F). This permits FIR(F) to be reinitialized in step 485 and for the stored information in FIRS(F) to be repeatedly sent (typically 500 times) to the host computer 14

10   in step 473 until FIRS(F) is updated the next time in step 483.

       In step 485, reinitialization to zero of index Nl, second accumulator variable Ml, and digital filter sum-of-squares accumulator FIR(F) occurs, whence RETURN 471 is reached.

15   In view of the above, it will be seen that the several objects of the invention are achieved and other advantageous results attained.

       As various changes could be made in the above con-structions without departing from the scope of the invention,

20   it is intended that all matter contained in the above descrip-tion or shown in the accompanying drawings shall be interpre-ted as illustrative and not in a limiting sense.

<u>Claims</u>   *57*

WHAT IS CLAIMED IS:

1. A hearing aid comprising:

a microphone for generating an electrical output from sounds
external to a user of the hearing aid;

an electrically driven receiver for emitting sound into the
5   ear of the user of the hearing aid; and

means for driving the receiver in a self-generating mode acti-
vated by a first set of signals supplied externally of the
hearing aid to cause the receiver to emit sound having at
least one parameter controlled by the first set of externally
10 supplied signals and for then driving the receiver in a fil-
tering mode, activated by a second set of signals supplied
externally of the hearing aid, with the output of the external
microphone filtered according to filter parameters established
by the second set of the externally supplied signals.

2. A hearing aid having a body adapted to be placed
in communication with an ear canal, the hearing aid body
having an external microphone sensitive to external sound, and
a receiver for supplying sound to the ear canal,
5   the hearing aid comprising:

a probe microphone in the hearing aid body for sensing the
sound present in the ear canal; and

means connected to the external microphone and said probe
microphone for driving the receiver in response to both the

58

10   external microphone and said probe microphone, and for gene-
rating a digital signal for external use in adjusting the per-
formance of the hearing aid, the digital signal representing
at least one parameter of the sound sensed by the probe
microphone.

3.   The hearing aid as set forth in claim 2 wherein
the driving and generating means comprises means for filtering
the output of the external microphone according to filter
parameters establishing the maximum power output of the

5   hearing aid as a function of frequency and for also generating
a second digital signal for external use in adjusting the per-
formance of the hearing aid, the second digital signal repre-
senting the number of times as a function of frequency that
the established maximum power output of the hearing aid occurs

10   in a predetermined period.

. 4.   A hearing aid having a body adapted to be placed
in communication with an ear canal, the hearing aid body
having an external microphone sensitive to external sound, and
a receiver for supplying sound to the ear canal,

5   the hearing aid comprising:

a probe microphone in the hearing aid body for sensing the
sound present in the ear canal; and

means connected to the external microphone for filtering, then
limiting, and then filtering the output of the external micro-

10   phone according to a set of internal parameters and for self-
adjusting at least one of the internal parameters as a func-
tion of the output of the probe microphone, thereby to drive
the receiver.

59

5.   A hearing aid for connection to an external
source of programming signals and having a body adapted to be
placed in communication with an ear canal, the hearing aid
body having an external microphone sensitive to external
5   sound, and a receiver for supplying sound to the ear canal,
the hearing aid comprising:

a probe microphone in the hearing aid body for sensing the
sound present in the ear canal; and

digital computing means in the hearing aid and coupled to the
10   external microphone, to said probe microphone and to the
receiver, and adapted for connection to the external source of
programming signals, said digital computing means comprising
means for loading and executing entire programs represented by
the signals and thereby utilizing said probe microphone, the
15   external microphone and the receiver for hearing testing and
digital filtering.

6.   A system for compensating hearing deficiencies
of a patient, comprising:

a hearing aid having an external microphone, programmable
means for filtering the output of the external microphone, and
5   a receiver driven by the programmable filtering means for
emitting sounds into the ear of the patient;

means for sensing responses of the patient to sounds from the
receiver; and

means communicating with the hearing aid and the sensing
10   means, for selectively generating a first set of signals to
cause the programmable filtering means in the hearing aid to
operate so that the receiver emits sounds having a parameter

60

controlled by the first set of signals, and for then generat-
ing in response to said sensing means a second set of signals
15   determined from the controlled parameter and the responses of
the patient to the sounds with the controlled parameter to
establish filter parameters in the programmable filtering
means to cause it to filter the output of the external micro-
phone and to drive the receiver with the filtered output
20   thereby ameliorating the hearing deficiencies of the patient.

        7.   A system for compensating hearing deficiencies
of a patient, comprising:

a hearing aid having an external microphone, a programmable
digital computer in the hearing aid and fed by the external
5   microphone, a receiver fed by the programmable digital com-
puter for emitting sounds into the ear of the patient, and a
probe microphone for sensing the actual sound in the ear of
the patient;

a data link; and

10   means for selectively supplying at least a first set and a
subsequent second set of digital signals to said data link,
said data link communicating the digital signals to said pro-
grammable digital computer of said hearing aid;

said programmable digital computer comprising means for selec-
15   tively driving said receiver so that at least one sound for
hearing testing is emitted into the ear in response to the
first set of digital signals, for supplying to said data link
a third set of digital signals representing a parameter of the
output of said probe microphone, and for subsequently filter-
20   ing the output of said external microphone in response to the
subsequently supplied second set of digital signals to drive

61

said receiver in a manner adapted for ameliorating the hearing
deficiencies of the patient.

        8.   For use in a system for compensating hearing
deficiencies of a patient, including a hearing aid having an
external microphone, a digital computer in the hearing aid fed
by the external microphone, a receiver fed by the digital com-

5   puter for emitting sounds into the ear of the patient, and a
probe microphone for sensing the actual sound in the ear of
the patient, signal supplying apparatus comprising:

interface means for performing two-way digital serial communi-
cation with the digital computer in the hearing aid; and

10   means for initiating transmission of a first set of signals
from said interface means to the hearing aid to cause the
digital computer in the hearing aid to operate so that the
receiver emits sounds having an adjustable parameter, for
obtaining, through the interface means, data representing

15   values of the adjustable parameter of the sounds as sensed by
the probe microphone, and for then initiating transmission
from said interface means of a second set of signals deter-
mined at least in part from the values of the parameter of the
sensed sounds to cause the digital computer in the hearing aid

20   to filter the output of the external microphone and drive the
receiver with the filtered output, thereby ameliorating the
hearing deficiencies of the patient.

        9.   Signal supplying apparatus as set forth in claim
8 further comprising a terminal connected to the initiating
means for displaying and adjusting the filtering performance
of the hearing aid resulting from the transmission

5   ·of the second set of signals.

62

10.   A method for compensating hearing deficiencies
of a patient with a hearing aid having an external microphone,
electronic means for processing the output of the external
microphone, and a receiver driven by the electronic processing
5   means for emitting sound into the ear of the patient, compris-
ing the steps of:

selectively supplying a first set of signals to the hearing
aid to cause the electronic processing means to operate so
that the receiver emits sound having a parameter controlled by
10   the first set of signals;

sensing and electrically storing representations of responses
of the patient to the sound; and

supplying a second set of signals determined from the at least
one controlled parameter of the sound and the representations
15   of the patient responses to the sound with the controlled
parameter to cause the electronic processing means to filter
the output of the external microphone and drive the receiver
with the filtered output, thereby ameliorating the hearing
deficiencies of the patient.

FIG.1

FIG.2

FIG.3

FIG.3A

FIG.4

FIG.5

FIG. 6

CALIBRATE FOR EAR IMPEDANCE

BEGIN ~225

_209_

DOWN LOAD REPORT 1 ~227 → AID

INPUT AND STORE CALIBRATION DATA OF AID ~229 ← AID

DOWN LOAD STIMULUS GENERATOR AND REPORT 2 ~231 → AID

TERMINAL → SELECT NEW TEST FREQ. COMPUTE TEST FREQ AND AMPL. COEFFICIENTS ~233

SEND FREQ, AMPL COEFFICIENTS ~235 → AID

INPUT M, STORE $SPL(F) = \sqrt{M/N_M}/HP(F)$ ~237 ← AID

NO ← DONE ? ~239

YES ~241

SCALING:
DO FOR ALL F:
$SC(F) = \dfrac{SPL(F)}{HR(F) \cdot A}$

RETURN ~243

FIG.7   AUDITORY AREA   *211*

BEGIN ~261

DOWNLOAD DIGITAL FILTER INCL. REPORT 2
FLAT RESPONSE, NO LIMITING ~263 ⟹ AID

OUTPUT IRU GRAPHICS
FOR THR, MCL, UCL ~265 ⟹ IRU

FIG.9

SELECT AND PRESENT
TEST SOUND ~267 ⟹ ATS

READ PATIENT
RESPONSE ~269 ⟵ IRU

RES-
PONSE
? ~271   YES ⟶ INPUT M AND STORE VALUES IN dB OF
SPL(F,RESPONSE)=$\sqrt{M/N_M}$/HP(F) ~275 ⟵ AID

NO

273 ~ NO / TIME
UP ?

YES

NO ⟵ STOP
TEST
? ~277

FIG.8

YES

ESTIMATE UCL(F), MCL(F), THR(F)
FROM VALUES OF SPL(F,RESPONSE) ~279

FREQ. RANGE
1 2 3 ··· R

CALCULATE, L(F), G1(F), G2(F)
AND DOWNLOAD DIGITAL
FILTER WITH REPORT 3 ~281 ⟹ AID

CALCULATE AI ~283

TERMINAL
AND
PLOTTER ⟵ DISPLAY GRAPH OF AUDITORY
AREA, HEARING AID
RESPONSE AND RESULTING AI,
L(F), G1(F), G2(F), STORE AI,
L(F), G1(F), G2(F) IN
PATIENT DATABASE ~285

RETURN ~287

FIG.10

SPEECH INTELLIGIBILITY

213

(BEGIN) —291

—293

TERMINAL ⟶ INPUT LIST ID

—295

OUTPUT IRU GRAPHICS
FOR RESPONSE CHOICES ⟶ IRU

—297

SEND SELECTED SPEECH
SAMPLE FROM ID LIST ⟶ ATS

—299

READ M, CA, FIRS (F),
LIMCNT (F) ⟵ AIO

—301

PROCESS LIMCNT(F) VALUES
OVER SPEECH SAMPLE

—303

READ PATIENT
RESPONSE ⟵ IRU

—305

TERMINAL ⟵ DISPLAY STIMULUS-RESPONSE
AND SIGNAL LEVEL DATA

—307

NO ⟵ ◇ TEST DONE? ◇

YES —309

CALC % CORRECT

—311

DISPLAY AI, LIST ID
PREDICTED & ACTUAL % CORRECT

—313

STORE AI, LIST ID, ACTUAL &
PREDICTED % CORRECT, AND
COMPLETE TEST RECORD
IN PATIENT DATA BASE

—315

(RETURN)

FIG.11

INTERACTIVE FINE ADJUSTMENT _____ 215

FIG.12

DSP
DOWNLOAD
MONITOR

START — 351

355 P=0 — 353

HOST → READ ADRO AND NUMBER OF BYTES NR

HOST → INPUT A BYTE — 357

STORE BYTE AT ADDRESS (ADRO+P) — 359

P=P+I — 361

P=NR ? — 363
NO

YES

BEGIN EXECUTION AT ADRO — 365

FIG.13

ROM 117 → MONITOR

JMP ADRI — ADRO

COEFF SPACE

ADRI

DSP PROGRAM SPACE

RAM 115

FIG.14

STIMULUS GENERATOR

BEGIN — 371

SET A   M=0   J=2
Y(0)=0   N=0
Y(1) = sin(2πfΔt)
C=2 cos(2πfΔt) — 373

$Y(J_{MOD3}) = C \times Y((J-1)_{MOD3}) - Y((J-2)_{MOD3})$ — 375

377 — $S = A \times Y(J_{MOD3})$

EN: DAC OUTPUT S
EN SHI OR SH2 — 379

J=(J+I)_{MOD3} — 381

EXECUTE REPORT 2 — 383 → HOST

385 WAIT

FIG.15

REPORT 1

BEGIN —391

ADDRESS SERIAL INTERFACE —393

OUTPUT CALIBRATIONS IN DSP MEMORY ⟹ HOST —395

END —397

FIG.16

REPORT 2

BEGIN —401

ADDRESS CONTROL LATCH —403

MUX: PROBE MIC
EN. S/H - IN
EN ADC
INPUT SI —405

$M = M + SI^2$
$N = N + 1$ —407

$N = N_M$? —409

YES

NO

ADDRESS SERIAL INTERFACE; OUTPUT M ⟹ HOST —413

N = 0
M = 0 —415

411 — RETURN

FIG.17
DIGITAL
FILTER

BEGIN — 421

— 423

N = 0; M = 0; M1 = 0; N1 = 0; I = 31;
FIR(F) = 0, FIRS(F) = 0
CA = 1
INIT S2(I), LIM(I,F) TABLES   INIT DAC
                                     LIMCNT(F) = 0

— 425

EXECUTE REPORT 2 OR 3 ⟹ HOST

F = 1 — 427

ADDRESS CONTROL LATCH — 429

MUX: EXT MIC; EN S/H IN; EN ADC;
INPUT VALUE, EXPAND AND STORE AT S2(I) — 431

$FIR1 = G1(F) \sum_{J=0}^{31} C_J(F) * S2(I-J)_{MOD32}$ — 433

IF FIR1 > 0,
LIM(I,F) = MIN(FIR1, L(F))
IF FIR1 < 0
LIM(I,F) = MAX(FIR1, -L(F)) — 435

F = F+1

448

$\begin{array}{c} FIR1 \\ > L(F) \\ ? \end{array}$ — 437

YES

NO

LIMCNT(F)
= LIMCNT(F)
+1 — 439

$FIR2(F) = G2(F) \sum_{J=0}^{31} C_J(F) * LIM(I-J,F)_{MOD 32}$

— 441

$FIR(F) = FIR(F) + FIR2^2(F)$ — 445

NO $\begin{array}{c} F = 4 \\ ? \end{array}$ — 447

YES

$I = (I+1)_{MOD32}$ — 457

FIRA = FIR2(1) + FIR2(2); FIRA = FIRA·CA — 449

EN: DAC
OUTPUT FIRA
EN S/H 1 — 451

FIR B = FIR2(3) + FIR2(4); FIRB = FIRB·CA — 453

EN DAC; OUTPUT
FIR B; EN S/H 2 — 455

FIG.18

REPORT 3

BEGIN ─ 461

ADDRESS
CONTROL ─ 463
LATCH

MUX:PROBE MIC
EN S/H-IN ─ 465
EN ADC
INPUT SI

$M = M + SI^2$
$N = N + 1$ ─ 467

469
$N = N_M$? ──── YES

473

ADDRESS SERIAL
INTERFACE;
OUTPUT M, FIRS(F), ───⇒ HOST
CA, LIMCNT(F)

475
$N=0, NI=NI+1, MI=MI+M$
$LIMCNT(F) = 0$ (ALL F)

$M=0$ ─ 477

479
NO ─── $NI=NMI$? ── 479

YES

481

CALCULATE CA FROM FIR(F) AND MI
LIMIT CA TO RANGE 0.5 TO 2.0

FIRS(F) = FIR(F) ─ 483
(ALL F)

485
$NI=0; MI=0; FIR(F)=0$

RETURN ─ 471

INTERNATIONAL SEARCH REPORT

International Application No PCT/US 85/01539

I. CLASSIFICATION OF SUBJECT MATTER (if several classification symbols apply, indicate all) *

According to International Patent Classification (IPC) or to both National Classification and IPC

IPC^4: H 04 R 25/00; A 61 B 5/12

II. FIELDS SEARCHED

Classification System	Minimum Documentation Searched [7]
	Classification Symbols
IPC^4	H 04 R A 61 B

Documentation Searched other than Minimum Documentation
to the Extent that such Documents are Included in the Fields Searched [8]

III. DOCUMENTS CONSIDERED TO BE RELEVANT [9]

Category *	Citation of Document, [11] with indication, where appropriate, of the relevant passages [12]	Relevant to Claim No. [13]
X Y A	DE, A, 3205685 (R. BOSCH) 25 August 1983, see the whole document --	 1,2,4-6,10 7,8 3
Y A	EP, A, 0071845 (SIEMENS) 16 February 1983, see claims, figures --	7 1,2,4-6,8, 10
Y A	Medical & Biological Engineering, volume 13, nr. 5, September 1975, London, (GB) E.L. Le Page:"An online sampled-data waveform control system", pages 637-643, see abstract; page 638, right-hand column line 22 - page 640, line 23; figures 1,2 --	 8 1,2,4-6,9, 10
A	DE, B, 2716336 (SIEMENS A.G.) 6 July 1978, see column 4, line 34 - column 6, line 44; figures --	1,2,4-8,10

* Special categories of cited documents: [10]
"A" document defining the general state of the art which is not considered to be of particular relevance
"E" earlier document but published on or after the international filing date
"L" document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)
"O" document referring to an oral disclosure, use, exhibition or other means
"P" document published prior to the international filing date but later than the priority date claimed

"T" later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention
"X" document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step
"Y" document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art.
"&" document member of the same patent family

IV. CERTIFICATION

Date of the Actual Completion of the International Search	Date of Mailing of this International Search Report
15th November 1985	1 0 DEC. 1985
International Searching Authority	Signature of Authorized Officer
EUROPEAN PATENT OFFICE	G.L.M. Kruvdenberg

Form PCT/ISA/210 (second sheet) (January 1985)

III. DOCUMENTS CONSIDERED TO BE RELEVANT (CONTINUED FROM THE SECOND SHEET)		
Category*	Citation of Document, with indication, where appropriate, of the relevant passages	Relevant to Claim No
A	US, A, 4188667 (D. GRAUPE) 12 February 1980, see claims; column 7, lines 28-46 ; column 8, line 27 - column 9, line 44; figures	1,2,4-8,10
A	EP, A, 0064042 (MANGOLD RÅDAVÅGEN) 3 November 1982, see claims; column 8, line 35 - column 9, line 2; figures	1,2,4-8,10
A	EP, A, 0010168 (R. BOSCH) 30 April 1980, see figures; claims	1,2,4-6,10
A	WO, A, 83/02212 (A/S DANAVOX) 23 June 1983, see claims; figures	1,2,4-6,10

This Annex lists the patent family members relating to the
patent documents cited in the above-mentioned international
search report. The members are as contained in the European
Patent Office EDP file on 29/11/85

The European Patent Office is in no way liable for these
particulars which are merely given for the purpose of
information.

Patent document cited in search report	Publication date	Patent family member(s)		Publication date
DE-A- 3205685	25/08/83	JP-A-	58151800	09/09/83
		US-A-	4471171	11/09/84
EP-A- 0071845	16/02/83	DE-A-	3131193	24/02/83
		JP-A-	58034700	01/03/83
		US-A-	4508940	02/04/85
DE-B- 2716336	06/07/78	NL-A-	7713292	17/10/78
		FR-A,B	2387563	10/11/78
		US-A-	4187413	05/02/80
		GB-A-	1582823	14/01/81
		CH-A-	623968	30/06/81
		CA-A-	1118881	23/02/82
US-A- 4188667	12/02/80	NL-A-	7701950	25/08/77
		DE-A-	2707607	01/09/77
		JP-A-	52125251	20/10/77
EP-A- 0064042	03/11/82	SE-A-	8102466	17/10/82
		JP-A-	57185800	16/11/82
		SE-B-	428167	06/06/83
		US-A-	4425481	10/01/84
		CA-A-	1176366	16/10/84
EP-A- 0010168	30/04/80	DE-A-	2844218	24/04/80
		AT-B-	E4365	15/08/83
WO-A- 8302212	23/06/83	EP-A-	0097184	04/01/84